# Distributed Multilevel Diversity Coding

Zhiqing Xiao, Jun Chen, Member, IEEE, Yunzhou Li, Member, IEEE, and Jing Wang, Member, IEEE

Abstract—In distributed multilevel diversity coding, K correlated sources (each with K components) are encoded in a distributed manner such that, given the outputs from any  $\alpha$  encoders, the decoder can reconstruct the first  $\alpha$  components of each of the corresponding  $\alpha$  sources. For this problem, the optimality of a multilayer Slepian–Wolf coding scheme based on binning and superposition is established when  $K \leq 3$ . The same conclusion is shown to hold for general K under a certain symmetry condition, which generalizes a celebrated result by Yeung and Zhang.

*Index Terms*—Data compression, diversity coding, entropy inequality, Lagrange multiplier, linear programming, rate region, Slepian-Wolf, superposition.

#### I. INTRODUCTION

**\checkmark** ONSIDER the scenario where K correlated sources  $U_1, U_2, \cdots, U_K$  are compressed by K sensors in a distributed manner and then forwarded to a fusion center for joint reconstruction. This is exactly the classical distributed data compression problem, for which Slepian-Wolf coding [1], [2] is known to be rate-optimal. However, to attain this best compression efficiency, encoding at each sensor is performed under the assumption that all the other sensors are functioning properly; as a consequence, inactivity of one or more sensors typically leads to a complete decoding failure at the fusion center. Alternatively, each sensor can compress its observation using conventional point-to-point data compression methods without capitalizing on the correlation among different sources so that the maximum system robustness can be achieved. In view of these two extreme cases, a natural question arises whether there exists a tradeoff between compression efficiency and system robustness in distributed data compression.

One approach to realize this tradeoff is as follows. Specifically, we decompose each  $U_k$  into K components  $U_{k,1}, U_{k,2}, \dots, U_{k,K}$ , ordered according to their importance,

Manuscript received April 30, 2015; revised September 2, 2015; accepted September 6, 2015. Date of publication September 9, 2015; date of current version October 16, 2015. Z. Xiao, Y. Li, and J. Wang were supported by the National Basic Research Program of China under Grant 2013CB329002, the National High Technology Research and Development Program of China under Grant 2014AA01A703, the National Science and Technology Major Project under Grant 2014ZX03003002, the Program for NCET in University under Grant NCET-13-0321, the International Science and Technology Cooperation Program under Grant 2014DFT10320, and the Tsinghua Research Funding under Grant 2015Z02-3. Z. Xiao was supported by Tsinghua Scholarship for Overseas Graduate Studies under Grant 2014057. J. Chen was supported by the Natural Science and Engineering Research Council of Canada under a Discovery Grant.

Z. Xiao is with the Department of Electronic Engineering, Tsinghua University, Beijing 100084, China (e-mail: xzq.xiaozhiqing@gmail.com).

J. Chen is with the Department of Electrical and Computer Engineering, McMaster University, Hamilton, ON L8S 4K1, Canada (e-mail: junchen@ece.mcmaster.ca).

Y. Li and J. Wang are with the Research Institute of Information Technology, Tsinghua University, Beijing 100084, China (e-mail: liyunzhou@ tsinghua.edu.cn; wangj@tsinghua.edu.cn).

Communicated by T. Liu, Associate Editor for Shannon Theory. Digital Object Identifier 10.1109/TIT.2015.2477506 and encode them in such a way that, given the outputs from any  $\alpha$  sensors, the fusion center can reconstruct the first  $\alpha$  components of each of the corresponding  $\alpha$  sources. The aforedescribed two extreme cases correspond to  $(U_{k,1}, \dots, U_{k,K-1}, U_{k,K}) = (0, \dots, 0, U_k)$  and  $(U_{k,1}, U_{k,2}, \dots, U_{k,K}) = (U_k, 0, \dots, 0)$ , respectively. One can realize a flexible tradeoff between compression efficiency and system robustness by adjusting the amount of information allocated to different components. We shall refer to this problem as distributed multilevel diversity coding (D-MLDC) since it reduces to the well-known (symmetrical) multilevel diversity coding (MLDC) problem when  $U_{1,\alpha} = U_{2,\alpha} = \dots = U_{K,\alpha}$  almost surely for all  $\alpha$ .

The concept of MLDC was introduced by Roche [3] and more formally by Yeung [4] though research on diversity coding can be traced back to Singleton's work on maximum distance separable codes [5]. The symmetric version of this problem has received particular attention [6], and arguably the culminating achievement of this line of research is the complete characterization of the admissible rate region of symmetrical MLDC by Yeung and Zhang [7]. Some recent developments related to MLDC can be found in [8]–[11].

The goal of the present paper is to characterize the performance limits of D-MLDC, which, we hope, may provide some useful insights into the tradeoff between compression efficiency and system robustness in distributed data compression. More fundamentally, we aim to examine the principle of superposition [4] in the context of D-MLDC. Although superposition (or more generally, layering) is a common way to construct sophisticated schemes based on simple building blocks and often vields the best known achievability results. establishing the optimality of such constructions is rarely straightforward, especially when encoding is performed in a distributed manner. In fact, even for the centralized encoding setup studied in [7], the proof of the optimality of superposition is already highly non-trivial. This difficulty can be partly attributed to the fact that it is often a technically formidable task to extract layers from a generic scheme using information inequalities in a converse argument, even in cases where the use of layered constructions may appear rather natural.

From this perspective, our work can be viewed as an initial step towards a better understanding of layered schemes for distributed compression of correlated sources. We shall propose a multilayer Slepian-Wolf coding scheme based on binning and superposition, and establish its optimality for D-MLDC when  $K \leq 3$ . This scheme is also shown to be optimal for general K under a certain symmetry condition, which generalizes the aforementioned result by Yeung and Zhang on symmetrical MLDC [7]. The main technical difficulty encountered in our proof is that it appears to be infeasible to characterize the admissible rate region of D-MLDC by

0018-9448 © 2015 IEEE. Personal use is permitted, but republication/redistribution requires IEEE permission. See http://www.ieee.org/publications\_standards/publications/rights/index.html for more information.

deriving inner and outer bounds separately and then making a direct comparison based on their explicit expressions. To circumvent this difficulty, we follow the approach in [7], where the analysis of the inner bound and that of the outer bound are conceptually intertwined. Specifically, we analyze certain linear programs associated with the achievable rate region of the proposed scheme and leverage the induced Lagrange multipliers to establish the entropy inequalities that are needed for a matching converse. Since the problem considered here is more general than that in [7], the relevant linear programs and entropy inequalities are inevitably more sophisticated. It is worth mentioning that, in a broad sense, the strategy of determining an information-theoretic limit by connecting achievability and converse results to a common optimization problem (not necessarily linear) via duality has find applications far beyond MLDC (see [12]).

The rest of this paper is organized as follows. We state the basic definitions and the main results in Section II. Section III contains a high-level description of our general approach. The detailed proofs can be found in Sections IV and V. We conclude the paper in Section VI.

*Notation:* Random objects  $(X_v, v \in V)$  and  $(X_{v,v'}, v \in V, v' \in V')$  are sometimes abbreviated as  $X_V$  and  $X_{V,V'}$ , respectively. For two integers  $z_1, z_2 \in \mathbb{Z}$ , we define  $[z_1 : z_2] \triangleq \{z \in \mathbb{Z} : z_1 \le z \le z_2\}$ . The  $\tau$ -th smallest element of a finite set  $V \subseteq \mathbb{Z}$  is denoted by  $\langle V \rangle_{\tau}$ ; moreover, let  $\langle V \rangle_T \triangleq \{\langle V \rangle_{\tau} : \tau \in T\}$  for any  $T \subseteq [1 : |V|]$ , where |V| is the cardinality of V. We often do not distinguish between a singleton and its element.

#### **II. PROBLEM FORMULATION AND MAIN RESULTS**

## A. System Model

Let  $U_{k,[1:K]}$ ,  $k \in [1:K]$ , be K vector sources. We assume<sup>1</sup> that  $U_{[1:K]\alpha}$ ,  $\alpha \in [1:K]$ , are mutually independent whereas, for each  $\alpha$ , the components of  $U_{[1:K]\alpha}$  (i.e.,  $U_{k,\alpha}$ ,  $k \in [1:K]$ ) can be arbitrarily correlated. Let  $\{U_{[1:K][1:K]}(t)\}_{t=1}^{\infty}$  be i.i.d. copies of  $U_{[1:K][1:K]}$ .

An  $(n, (M_k, k \in [1 : K]))$  D-MLDC system consists of:

• *K* encoders, where encoder  $\text{Enc}_k$  ( $k \in [1 : K]$ ) maps the source sequence  $U_{k,[1:K]}^n$  to a symbol  $S_k$  in  $[1 : M_k]$ , i.e.,

$$\mathsf{Enc}_{k}: \prod_{\alpha=1}^{K} \mathcal{U}_{k,\alpha}^{n} \to [1:M_{k}],$$
$$U_{k,[1:K]}^{n} \mapsto S_{k},$$

•  $2^{K} - 1$  decoders, where decoder  $\text{Dec}_{V}$  ( $\emptyset \subseteq V \subseteq [1:K]$ ) produces a reconstruction of  $U_{V,[1:|V|]}^{n}$ , denoted by  $\hat{U}_{V,[1:|V|]}^{n}$ , based on  $S_{V}$ , i.e.,

$$\mathsf{Dec}_V : \prod_{k \in V} [1:M_k] \to \prod_{k \in V} \prod_{\alpha=1}^{|V|} \mathcal{U}_{k,\alpha}^n,$$
$$S_V \mapsto \hat{U}_{V,[1:|V|]}^n.$$

<sup>1</sup>This assumption can be relaxed to a certain extent and can be modified in various ways. In this paper we do not seek to present our results in their most general forms since the resulting statements and expressions may become rather unwieldy.



Fig. 1. System diagram for D-MLDC with K = 3.

A D-MLDC system with K = 3 is illustrated in Fig. 1.

## B. Admissible Rate Region

A rate tuple  $(R_k, k \in [1 : K])$  is said to admissible if, for any  $\epsilon > 0$ , there exists an  $(n, (M_k, k \in [1 : K]))$  D-MLDC system such that

(1) (Rate Constraints)

(2)

$$\frac{1}{n}\log M_k \le R_k + \epsilon, \quad k \in [1:K], \tag{1}$$

$$\Pr\left\{U_{V,[1:|V|]}^{n} \neq U_{V,[1:|V|]}^{n}\right\} \le \epsilon, \quad \emptyset \subsetneq V \subseteq [1:K].$$
(2)

The admissible rate region  $\mathcal{R}_K^*$  is defined as the set of all admissible rate tuples.

## C. Multilayer Slepian-Wolf Coding

We shall propose a D-MLDC scheme, which can be viewed as a natural extension of that in [7] to the distributed encoding setup. This scheme, termed multilayer Slepian-Wolf coding, includes two steps: intralayer coding and interlayer coding.

• *Intralayer Coding:* For each  $\alpha \in [1:K]$ , encoder k  $(k \in [1:K])$  compresses  $U_{k,\alpha}^n$  using the conventional binning scheme<sup>2</sup> of rate  $r_{k,\alpha}$ ; correct reconstruction of  $U_{k,\alpha}^n$ ,  $\alpha \in V$ , based on the corresponding bin indices is ensured (with high probability) for all  $V \subseteq [1:K]$  with  $|V| = \alpha$  if  $(r_{k,\alpha}, k \in [1:K]) \in \mathcal{R}_{K,\alpha}$ . Here

$$\mathcal{R}_{K,\alpha} \triangleq \left\{ \left( r_{k,\alpha}, k \in [1:K] \right) : \sum_{k \in V} r_{k,\alpha} \ge H \left( U_{V,\alpha} | U_{V',\alpha} \right), \\ V \in \mathbb{V}_{K,\alpha}, V' \in \mathbb{V}'_{K,\alpha} \left[ V \right] \right\}$$

 $^{2}$ Here one can in fact use universal Slepian-Wolf coding so that encoding and decoding can be performed without the knowledge of the source distribution [13].

with

 $\mathbb{V}_{K,\alpha} \triangleq \{ V \subseteq [1:K] : 1 \le |V| \le \alpha \},\$  $\mathbb{V}'_{K,\alpha}[V] \triangleq \{ V' \subseteq [1:K] \setminus V : |V'| + |V| = \alpha \}, \ V \in \mathbb{V}_{K,\alpha}.$ 

• *Interlayer Coding:* In this step, encoder k ( $k \in [1 : K]$ ) generates its output by combining the bin indices associated with  $U_{k,\alpha}^n$ ,  $\alpha \in [1 : K]$ , via superposition. Note that the resulting rate region

$$\mathcal{R}_{K} \triangleq \left\{ \sum_{\alpha=1}^{K} \left( r_{k,\alpha}, k \in [1:K] \right) : \\ \left( r_{k,\alpha}, k \in [1:K] \right) \in \mathcal{R}_{K,\alpha}, \quad \alpha \in [1:K] \right\}$$

is an inner bound of  $\mathcal{R}_{K}^{*}$ , i.e.,

$$\mathcal{R}_K \subseteq \mathcal{R}_K^*. \tag{3}$$

## D. Main Results

Our first main result shows that  $\mathcal{R}_K$  coincides with  $\mathcal{R}_K^*$  when  $K \leq 3$ .

Theorem 1:  $\mathcal{R}_K^* = \mathcal{R}_K$  for  $K \leq 3$ .

To state our second main result, we need the following definition.

Definition 1 (Symmetrical Source): We say that the distribution of  $U_{[1:K],[1:K]}$  is symmetrical entropy-wise if  $H(U_{V,\alpha}) = H(U_{V',\alpha})$  for all  $\alpha \in [1:K]$  and V,  $V' \subseteq [1:K]$  with |V| = |V'|.

It is worth noting that the symmetrical MLDC problem studied in [7] corresponds to the special case where  $H(U_{V,\alpha}) = H(U_{V',\alpha})$  for all  $\alpha \in [1:K]$  and  $\emptyset \subsetneq V, V' \subseteq [1:K]$ .

*Theorem 2:* If the distribution of  $U_{[1:K],[1:K]}$  is symmetrical entropy-wise, then  $\mathcal{R}_{K}^{*} = \mathcal{R}_{K}$ .

## III. OUTLINE OF A GENERAL APPROACH

In this section we attempt to give an outline of our general approach, which is in principle not restricted to the cases covered by Theorems 1 and 2. On a conceptual level, this approach was originated in [7] (and made more evident in [10]). It consists of three major steps:

- 1) characterize the supporting hyperplanes of  $\mathcal{R}_K$  (more precisely, the supporting hyperplanes of  $\mathcal{R}_{K,\alpha}$ ,  $\alpha \in [1:K]$ ) via the analysis of the corresponding linear programs;
- establish a class of entropy inequalities based on the Lagrange multipliers induced by the aforementioned linear programs;
- 3) derive a tight outer bound on  $\mathcal{R}_K$  by leveraging these entropy inequalities.

#### A. Linear Program

Each supporting hyperplane of  $\mathcal{R}_{K,\alpha}$  is associated with a linear program

$$\mathsf{LP}_{K,\alpha}^{\mathbf{w}}: \min \sum_{k=1}^{K} w_k r_{k,\alpha}$$
  
over  $r_{k,\alpha}, k \in [1:K],$ 

s.t. 
$$\sum_{k \in V} r_{k,\alpha} \ge H\left(U_{V,\alpha} | U_{V',\alpha}\right),$$
$$V \in \mathbb{V}_{K,\alpha}, V' \in \mathbb{V}'_{K,\alpha} [V],$$

where  $\mathbf{w} \triangleq (w_k, k \in [1:K]) \in \mathbb{R}_+^K$ . It often suffices to consider the case where the weights  $w_k, k \in [1:K]$ , are ordered. For this reason, we define

$$\mathbb{W}_{K} \triangleq \Big\{ \mathbf{w} : w_{1} \ge w_{2} \ge \cdots \ge w_{K} \ge w_{K+1} \triangleq 0 \Big\}.$$

Moreover, to facilitate subsequent analysis, we introduce the following partition<sup>3</sup> of  $\mathbb{W}_K$  for each  $\alpha \in [2 : K]$ :

$$\mathbb{W}_{K,\alpha}^{(0)} \triangleq \left\{ \mathbf{w} \in \mathbb{W}_{K} : w_{1} \leq \frac{1}{\alpha - 1} \sum_{k=2}^{K} w_{k} \right\},$$
$$\mathbb{W}_{K,\alpha}^{(l)} \triangleq \left\{ \mathbf{w} \in \mathbb{W}_{K} : w_{l} > \frac{1}{\alpha - l} \sum_{k=l+1}^{K} w_{k} \right\},$$
and  $w_{l+1} \leq \frac{1}{\alpha - (l+1)} \sum_{k=l+2}^{K} w_{k} \right\},$  $l \in [1 : \alpha - 2],$ 
$$\mathbb{W}_{K,\alpha}^{(\alpha-1)} \triangleq \left\{ \mathbf{w} \in \mathbb{W}_{K} : w_{\alpha-1} > \sum_{k=\alpha}^{K} w_{k} \right\}.$$

We set  $\mathbb{W}_{K,1}^{(0)} \triangleq \mathbb{W}_K$ .

Definition 2 (Optimal Lagrange Multiplier): We say<sup>4</sup> that  $(c_{V|V',\alpha}, V \in \mathbb{V}_{K,\alpha}, V' \in \mathbb{V}'_{K,\alpha}[V])$  is an optimal Lagrange multiplier of  $\mathsf{LP}^{\mathbf{w}}_{K,\alpha}$  with  $\mathbf{w} \in \mathbb{R}^{K}_{+}$  if

$$\sum_{V \in \mathbb{V}_{K,a}} \sum_{V' \in \mathbb{V}'_{K,a}[V]} c_{V|V',\alpha} H\left(U_{V,\alpha}|U_{V',\alpha}\right) = f_{\alpha}^{\mathbf{w}}, \quad (4)$$
$$\sum_{V \in \mathbb{V}_{K,\alpha}: k \in V} \sum_{V' \in \mathbb{V}'_{K,\alpha}[V]} c_{V|V',\alpha} = w_k, \quad k \in [1:K], \quad (5)$$

 $c_{V|V',\alpha} \ge 0, \quad V \in \mathbb{V}_{K,\alpha}, \quad V' \in \mathbb{V}'_{K,\alpha}[V],$ 

where  $f_{\alpha}^{\mathbf{w}}$  denotes the optimal value of  $\mathsf{LP}_{K,\alpha}^{\mathbf{w}}$ .

It is in general not easy to find optimal solution  $\begin{pmatrix} r_{k,\alpha}^{\text{opt}}, k \in [1:K] \end{pmatrix}$  and optimal Lagrange multiplier  $(c_{V|V',\alpha}, V \in \mathbb{V}_{K,\alpha}, V' \in \mathbb{V}'_{K,\alpha}[V])$  for a given  $\mathsf{LP}^{\mathsf{w}}_{K,\alpha}$  (see Section IV for a detailed analysis of  $\mathsf{LP}^{\mathsf{w}}_{3,2}$ ). However, the task becomes relatively straightforward when  $\alpha = 1$  or  $\alpha = K$  as shown by the following two lemmas (which can be proved via direct verification).

*Lemma 1:* For linear program  $\mathsf{LP}_{K,1}^{\mathbf{w}}$  with  $\mathbf{w} \in \mathbb{R}_{+}^{K}$ ,  $\begin{pmatrix} r_{k,1}^{\text{opt}}, k \in [1:K] \end{pmatrix}$  is an optimal solution and  $(c_{V|\emptyset,1}, V \in \mathbb{V}_{K,1})$  is the unique optimal Lagrange multiplier, where

$$r_{k,1}^{\text{opt}} \triangleq H(U_{k,1}), \quad k \in [1:K],$$
  
$$c_{\{k\}|\emptyset,1} \triangleq w_k, \quad k \in [1:K].$$

<sup>3</sup>For  $\mathbf{w} \in \mathbb{W}_K$ , we have  $w_l > \frac{1}{\alpha - l} \sum_{k=l+1}^K w_k \Rightarrow w_{l'} > \frac{1}{\alpha - l'} \sum_{k=l'+1}^K w_k$ ,  $l' \in [1:l]$ , and  $w_l \leq \frac{1}{\alpha - l} \sum_{k=l+1}^K w_k \Rightarrow w_{l'} \leq \frac{1}{\alpha - l'} \sum_{k=l'+1}^K w_k$ ,  $l' \in [l:\alpha - 1]$ . Therefore,  $\mathbb{W}_{K,\alpha}^{(0)}, \cdots, \mathbb{W}_{K,\alpha}^{(\alpha - 1)}$  indeed form a partition of  $\mathbb{W}_K$ .

<sup>4</sup>It can be shown that  $(c_{V|V',\alpha}, V \in \mathbb{V}_{K,\alpha}, V' \in \mathbb{V}'_{K,\alpha}[V])$  is an optimal Lagrange multiplier of  $\mathsf{LP}^{\mathbf{w}}_{K,\alpha}$  if and only if it is an optimal solution to the (asymmetric) dual problem of  $\mathsf{LP}^{\mathbf{w}}_{K,\alpha}$ .

*Lemma 2:* For linear program  $\mathsf{LP}_{K,K}^{\mathbf{w}}$  with  $\mathbf{w} \in \mathbb{W}_K$ ,  $(r_{k,K}^{\text{opt}}, k \in [1:K])$  is an optimal solution and  $(c_{V|[1:K]\setminus V,K}, V \in \mathbb{V}_{K,K})$  is an optimal Lagrange multiplier, where

$$r_{k,K}^{\text{opt}} \triangleq H\left(U_{k,K}|U_{[k+1:K],K}\right), \quad k \in [1:K],$$

$$c_{[1:k]|[k+1:K],K} \triangleq w_k - w_{k+1}, \quad k \in [1:K],$$

$$c_{V|[1:K]\setminus V,K} \triangleq 0, \quad \text{otherwise.}$$

The general case  $\mathbf{w} \in \mathbb{R}^{K}_{+}$  can be reduced to the case  $\mathbf{w} \in \mathbb{W}_{K}$  via suitable relabelling.

## B. Entropy Inequality

In this step we aim to establish a class of entropy inequalities needed for a matching converse by exploiting the properties of optimal Lagrange multipliers of  $LP_{K,\alpha}^{\mathbf{w}}$ ,  $\alpha \in [1:K]$ . More precisely, we shall identify suitable conditions under which there exist optimal Lagrange multipliers  $(c_{V|V',\alpha}, V \in \mathbb{V}_{K,\alpha}, V' \in \mathbb{V}'_{K,\alpha}[V])$ ,  $\alpha \in [1:K]$ , such that

$$\sum_{V \in \mathbb{V}_{K,\alpha'}} \sum_{V' \in \mathbb{V}'_{K,\alpha'}[V]} c_{V|V',\alpha'} H\left(X_V|X_{V'}\right)$$
  

$$\geq \sum_{V \in \mathbb{V}_{K,\alpha}} \sum_{V' \in \mathbb{V}'_{K,\alpha}[V]} c_{V|V',\alpha} H\left(X_V|X_{V'}\right)$$
(6)

for all  $X_{[1:K]}$  and  $\alpha \geq \alpha'$ .

The following lemma indicates that (6) always holds when  $\alpha' = 1$ .

Lemma 3: We have

$$\sum_{V \in \mathbb{V}_{K,1}} c_{V|\emptyset,1} H(X_V)$$

$$\geq \sum_{V \in \mathbb{V}_{K,a}} \sum_{V' \in \mathbb{V}_{K,a}'} c_{V|V',a} H(X_V|X_{V'})$$

for all  $X_{[1:K]}$ , where  $(c_{V|\emptyset,1}, V \in \mathbb{V}_{K,1})$  and  $(c_{V|V',\alpha}, V \in \mathbb{V}_{K,\alpha}, V' \in \mathbb{V}'_{K,\alpha}[V])$  are optimal Lagrange multipliers of  $\mathsf{LP}^{\mathbf{w}}_{K,1}$  and  $\mathsf{LP}^{\mathbf{w}}_{K,\alpha}$ , respectively.

*Proof:* According to (5),

$$c_{\{k\}|\emptyset,1} = w_k$$
  
= 
$$\sum_{V \in \mathbb{V}_{K,\alpha}: k \in V} \sum_{V' \in \mathbb{V}'_{K,\alpha}[V]} c_{V|V',\alpha}, \quad k \in [1:K].$$
(7)

It can be verified that

$$\sum_{V \in \mathbb{V}_{K,1}} c_{V|\emptyset,1} H(X_V)$$

$$= \sum_{k=1}^{K} c_{\{k\}|\emptyset,1} H(X_k)$$

$$= \sum_{k=1}^{K} \sum_{V \in \mathbb{V}_{K,\alpha}: k \in V} \sum_{V' \in \mathbb{V}'_{K,\alpha}[V]} c_{V|V',\alpha} H(X_k) \qquad (8)$$

$$= \sum_{V \in \mathbb{V}_{K,\alpha}} \sum_{V' \in \mathbb{V}'_{K,\alpha}[V]} c_{V|V',\alpha} \sum_{k \in V} H(X_k)$$

$$\geq \sum_{V \in \mathbb{V}_{K,a}} \sum_{V' \in \mathbb{V}'_{K,a}[V]} c_{V|V',a} H(X_V)$$
  
$$\geq \sum_{V \in \mathbb{V}_{K,a}} \sum_{V' \in \mathbb{V}'_{K,a}[V]} c_{V|V',a} H(X_V|X_{V'})$$

where (8) is due to (7). This completes the proof of Lemma 3.  $\blacksquare$ 

### C. Outer Bound

As shown by the following lemma, the existence of entropy inequalities (6) implies that  $\mathcal{R}_K$  is an outer bound of  $\mathcal{R}_K^*$ .

Lemma 4: If given any  $\mathbf{w} \in \mathbb{R}_+^K$ , there exist optimal Lagrange multipliers  $(c_{V|V',\alpha}, V \in \mathbb{V}_{K,\alpha}, V' \in \mathbb{V}'_{K,\alpha}[V]), \alpha \in [1:K]$ , such that (6) holds, then

$$\mathcal{R}_K^* \subseteq \mathcal{R}_K. \tag{9}$$

*Proof:* Let  $(R_k, k \in [1 : K])$  be an arbitrary admissible rate tuple. It suffices to show that

$$\sum_{k=1}^{K} w_k R_k \ge \sum_{\alpha=1}^{K} f_{\alpha}^{\mathbf{w}}, \tag{10}$$

from which (9) follows immediately. We shall prove via induction that, for any D-MLDC system satisfying (1) and (2),

$$\sum_{k=1}^{K} w_k \left( R_k + \epsilon \right) \ge \sum_{\alpha=1}^{\beta} f_{\alpha}^{\mathbf{w}} + \frac{1}{n} \sum_{V \in \mathbb{V}_{K,\beta}} \sum_{V' \in \mathbb{V}'_{K,\beta}[V]} c_{V|V',\beta} H \left( S_V | U_{[1:K][1:\beta]}^n, S_{V'} \right) - \beta \delta_{\epsilon} \sum_{k=1}^{K} w_k, \quad \beta \in [1:K],$$

$$(11)$$

where  $\delta_{\epsilon}$  tends to zero as  $\epsilon \to 0$ . One can deduce (10) from (11) by setting  $\beta = K$  and sending  $\epsilon \to 0$ .

It can be verified that

$$\sum_{k=1}^{K} w_k \left( R_k + \epsilon \right) \ge \frac{1}{n} \sum_{k=1}^{K} w_k \log M_k$$
$$\ge \frac{1}{n} \sum_{k=1}^{K} w_k H(S_k)$$
$$= \frac{1}{n} \sum_{V \in \mathbb{V}_{K,1}} c_{V|\emptyset,1} H(S_V), \qquad (12)$$

where (12) is due to the fact (see Lemma 1) that the optimal Lagrange multiplier  $(c_{V|\emptyset,1}, V \in \mathbb{V}_{K,1})$  is uniquely given by  $c_{\{k\}|\emptyset,1} \triangleq w_k, k \in [1:K]$ . Note that

$$H(S_{V}) \geq H(U_{V,1}^{n}) + H(S_{V}|U_{V,1}^{n}) - H(U_{V,1}^{n}|S_{V})$$
  

$$\geq H(U_{V,1}^{n}) + H(S_{V}|U_{V,1}^{n}) - n\delta_{\epsilon}$$
(13)  

$$\geq H(U_{V,1}) + H(S_{V}|U_{[1:K]1}^{n}) - n\delta_{\epsilon}, V \in \mathbb{V}_{K,1},$$
(14)

where (13) follows by (2) and Fano's inequality. Substituting (14) into (12) and invoking (4) proves (11) for  $\beta = 1$ . Now assume that (11) holds for  $\beta = B - 1$ . In view of (6), we have

$$\sum_{V \in \mathbb{V}_{K,B-1}} \sum_{V' \in \mathbb{V}'_{K,B-1}[V]} c_{V|V',B-1} H\left(S_{V}|U^{n}_{[1:K][1:B-1]}, S_{V'}\right)$$

$$\geq \sum_{V \in \mathbb{V}_{K,B}} \sum_{V' \in \mathbb{V}'_{K,B}[V]} c_{V|V',B} H\left(S_{V}|U^{n}_{[1:K][1:B-1]}, S_{V'}\right).$$
(15)

It can be verified that

$$H\left(S_{V}|U_{[1:K][1:B-1]}^{n}, S_{V'}\right) = H\left(U_{V,B}^{n}, S_{V}|U_{[1:K][1:B-1]}^{n}, S_{V'}\right) - H\left(U_{V,B}^{n}|U_{[1:K][1:B-1]}^{n}, S_{V}, S_{V'}\right) \geq H\left(U_{V,B}^{n}, S_{V}|U_{[1:K][1:B-1]}^{n}, S_{V'}\right) - n\delta_{\epsilon}, V \in \mathbb{V}_{K,B}, V' \in \mathbb{V}'_{K,B},$$
(16)

where (16) follows by (2) and Fano's inequality. Moreover,

$$H\left(U_{V,B}^{n}, S_{V}|U_{[1:K][1:B-1]}^{n}, S_{V'}\right) \\ \geq H\left(U_{V,B}^{n}|U_{[1:K][1:B-1]}^{n}, S_{V'}\right) + H\left(S_{V}|U_{[1:K][1:B]}^{n}, S_{V'}\right) \\ \geq H\left(U_{V,B}^{n}|U_{V',B}^{n}\right) + H\left(S_{V}|U_{[1:K][1:B]}^{n}, S_{V'}\right)$$
(17)

$$= H\left(U_{V,B}|U_{V',B}\right) + H\left(S_{V}|U_{[1:K][1:B]}^{n}, S_{V'}\right),$$
(18)

where (17) is due to the fact that  $U_{V,B}^n \leftrightarrow U_{V',B}^n \leftrightarrow (U_{[1:K][1:B]}^n, S_{V'})$  form a Markov chain. Continuing from (15),

$$\begin{split} \sum_{V \in \mathbb{V}_{K,B-1}} \sum_{V' \in \mathbb{V}'_{K,B-1}[V]} c_{V|V',B-1} H\left(S_{V}|U_{[1:K]_{1}[1:B-1]}^{n}, S_{V'}\right) \\ \geq n \sum_{V \in \mathbb{V}_{K,B}} \sum_{V' \in \mathbb{V}'_{K,B}[V]} c_{V|V',B} H\left(U_{V,B}|U_{V',B}\right) \\ &+ \sum_{V \in \mathbb{V}_{K,B}} \sum_{V' \in \mathbb{V}'_{K,B}[V]} c_{V|V',B} H\left(S_{V}|U_{[1:K]_{1}[1:B]}^{n}, S_{V'}\right) \\ &- n\delta_{\epsilon} \sum_{V \in \mathbb{V}_{K,B}} \sum_{V' \in \mathbb{V}'_{K,B}[V]} c_{V|V',B} H\left(U_{V,B}|U_{V',B}\right) \\ &\geq n \sum_{V \in \mathbb{V}_{K,B}} \sum_{V' \in \mathbb{V}'_{K,B}[V]} c_{V|V',B} H\left(S_{V}|U_{[1:K]_{1}[1:B]}^{n}, S_{V'}\right) \\ &- n\delta_{\epsilon} \sum_{k=1}^{K} \sum_{V \in \mathbb{V}_{K,B}: k \in V} \sum_{V' \in \mathbb{V}'_{K,B}[V]} c_{V|V',B} \\ &= nf_{B}^{\mathbf{w}} \\ &+ \sum_{V \in \mathbb{V}_{K,B}} \sum_{V' \in \mathbb{V}'_{K,B}[V]} c_{V|V',B} H\left(S_{V}|U_{[1:K]_{1}[1:B]}^{n}, S_{V'}\right) \\ &- n\delta_{\epsilon} \sum_{k=1}^{K} w_{k}, \end{split}$$
(20)

where (19) is due to (16) and (18), and (20) is due to (4) and (5). Combining (20) and the induction hypothesis proves (11) for  $\beta = B$ .

#### **IV. PROOF OF THEOREM 1**

Theorem 1 is trivially true when K = 1. The case K = 2 is a simple consequence of Lemma 3 and Lemma 4. Therefore, only the case K = 3 remains to be proved.

To this end, we shall give a detailed analysis of  $LP_{3,2}^{w}$ . First consider the following related linear program

$$\widetilde{\mathsf{LP}}_{3,2}^{\mathbf{w}}: \max \sum_{k=1}^{3} w_k r_{k,2}$$
  
over  $r_{k,2}, k \in [1:3],$   
s.t.  $r_{k,2} \ge \psi_{\{k\}}, k \in [1:3],$   
 $r_{i,2} + r_{j,2} \ge \psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}},$   
 $i, j \in [1:3], i \ne j,$ 

where  $\psi_V$ ,  $V \in \mathbb{V}_{3,2}$ , are non-negative real numbers. We say that  $(\tilde{c}_{V,2}, V \in \mathbb{V}_{3,2})$  is an optimal Lagrange multiplier of  $\widetilde{\mathsf{LP}}_{3,2}^{\mathbf{w}}$  if

$$\sum_{k=1}^{3} \tilde{c}_{\{k\},2} \psi_{\{k\}} + \sum_{i,j \in [1:3], i < j} \tilde{c}_{\{i,j\},2} \left( \psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}} \right) = \tilde{f}_{\psi}^{\mathsf{w}},$$
$$\sum_{V \in \mathbb{V}_{3,2}: k \in V} \tilde{c}_{V,2} = w_k, \quad k \in [1:3],$$
$$\tilde{c}_{V,2} \ge 0, \quad V \in \mathbb{V}_{3,2},$$

where  $\tilde{f}_{\psi}^{\mathbf{w}}$  denotes the optimal value of  $\widetilde{\mathsf{LP}}_{3,2}^{\mathbf{w}}$ . One can solve  $\widetilde{\mathsf{LP}}_{3,2}^{\mathbf{w}}$  with  $\mathbf{w} \in \mathbb{W}_3$  by considering 5 different cases (see Table I).

Now set

$$\begin{split} \psi_{\{k\}} &\triangleq H\left(U_{k,2}|U_{\nu_{k},2}\right), \quad k \in [1:3], \\ \psi_{\{i,j\}} &\triangleq \max\left\{H\left(U_{i,2},U_{j,2}\right) - \psi_{i} - \psi_{j},0\right\}, \\ i, j \in [1:3], \ i \neq j, \end{split}$$

where  $v_k$  is a maximizer of  $\max_{v \in [1:3] \setminus \{k\}} H(U_{k,2}|U_{v,2})$ . Moreover, define

$$\tilde{\mathcal{R}}_{3,2} \triangleq \left\{ \left( r_{k,2}, k \in [1:3] \right) : r_{k,2} \ge \psi_{\{k\}}, k \in [1:3], r_{i,2} + r_{j,2} \ge \psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}}, i, j \in [1:3], i \neq j \right\}$$

One can prove via direct verification that  $\mathcal{R}_{3,2}$  coincides with  $\tilde{\mathcal{R}}_{3,2}$ .

*Lemma 5:*  $\mathcal{R}_{3,2} = \tilde{\mathcal{R}}_{3,2}$ .

See Fig. 2 for illustrations of  $\mathcal{R}_{3,2}$  (i.e.,  $\tilde{\mathcal{R}}_{3,2}$ ), where the optimal solutions in Table I are highlighted.

*Lemma 6:* Let *i*, *j*, *k* be three distinct integers in [1 : 3]. (1)  $\psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}}$ 

$$= \begin{cases} H(U_{i,2}, U_{j,2}), & H(U_{i,2}, U_{j,2}) \ge \psi_{\{i\}} + \psi_{\{j\}}, \\ H(U_{i,2}|U_{k,2}) + H(U_{j,2}|U_{k,2}), \\ & H(U_{i,2}, U_{j,2}) < \psi_{\{i\}} + \psi_{\{j\}}. \end{cases}$$

(2) If 
$$\psi_{\{i,j\}} > \psi_{\{i,k\}} + \psi_{\{j,k\}}$$
, then

$$\psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}} = H(U_{i,2}, U_{j,2})$$



TABLE I LINEAR PROGRAM  $\widetilde{LP}_{3,2}^{W}$ 



Case 3

Case 5

 $\psi_{13} > \psi_{12} + \psi_{23}$ 

(3) If  $\psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}} = H(U_{i,2}|U_{k,2}) + H(U_{j,2}|U_{k,2}),$ then

$$\begin{split} \psi_{\{i\}} + \psi_{\{i,k\}} + \psi_{\{k\}} &= H\left(U_{i,2}, U_{k,2}\right), \\ \psi_{\{j\}} + \psi_{\{j,k\}} + \psi_{\{k\}} &= H\left(U_{j,2}, U_{k,2}\right). \\ Proof: \text{ See Appendix A.} \end{split}$$

Case 4

 $\psi_{23} > \psi_{12} + \psi_{13}$ 

According to Lemma 6, we have the following four cases for  $\psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}}$   $(i, j \in [1:3], i \neq j)$ : (Case A)

> $\psi_{\{1\}} + \psi_{\{1,2\}} + \psi_{\{2\}} = H(U_{1,2}, U_{2,2}),$  $\psi_{\{1\}} + \psi_{\{1,3\}} + \psi_{\{3\}} = H(U_{1,2}, U_{3,2}),$  $\psi_{\{2\}} + \psi_{\{2,3\}} + \psi_{\{3\}} = H(U_{2,2}, U_{3,2});$

TABLE II Optimal Lagrange Multipliers of  $\mathsf{LP}_{3,2}$  for All Possible Cases

Casa						
Case	$  c_{\{1\}} _{\{\nu_1\},2}$	$C{2}{\nu_2},2$	$C_{\{3\} \{\nu_3\},2}$	$C_{\{1,2\} \emptyset,2}$	$C_{\{1,3\} \emptyset,2}$	$C_{\{2,3\}} \emptyset,2$
1A	0	0	0	$\frac{1}{2}(w_1+w_2-w_3)$	$\frac{1}{2}(w_1 - w_2 + w_3)$	$\frac{1}{2}(-w_1+w_2+w_3)$
1B	0	$\frac{1}{2}(-w_1+w_2+w_3)$	$\frac{1}{2}(-w_1+w_2+w_3)$	$\frac{1}{2}(w_1+w_2-w_3)$	$\frac{1}{2}(w_1 - w_2 + w_3)$	0
1C	$\frac{1}{2}(w_1 - w_2 + w_3)$	0	$\frac{1}{2}(w_1 - w_2 + w_3)$	$\frac{1}{2}(w_1+w_2-w_3)$	0	$\frac{1}{2}(-w_1+w_2+w_3)$
1D	$\frac{1}{2}(w_1+w_2-w_3)$	$\frac{1}{2}(w_1+w_2-w_3)$	0	0	$\frac{1}{2}(w_1 - w_2 + w_3)$	$\frac{1}{2}(-w_1+w_2+w_3)$
2A	0	0	$-w_1 + w_2 + w_3$	$w_2$	$w_1 - w_2$	0
2B	0	0	$-w_1 + w_2 + w_3$	$w_2$	$w_1 - w_2$	0
2C	$w_1 - w_2$	0	$w_3$	$w_2$	0	0
3A	0	$-w_1 + w_2 + w_3$	0	$w_1 - w_3$	$w_3$	0
3B	0	$-w_1 + w_2 + w_3$	0	$w_1 - w_3$	$w_3$	0
3D	$w_1 - w_3$	$w_2$	0	0	$w_3$	0
4A	$w_1 - w_2 + w_3$	0	0	$w_2 - w_3$	0	$w_3$
4C	$w_1 - w_2 + w_3$	0	0	$w_2 - w_3$	0	$w_3$
4D	$w_1$	$w_2 - w_3$	0	0	0	$w_3$
5A	$w_1 - w_2 - w_3$	0	0	$w_2$	$w_3$	0
5B	$w_1 - w_2$	0	$w_3$	$w_2$	0	0
5C	$w_1 - w_2 - w_3$	0	0	$w_2$	$w_3$	0
5D	$w_1 - w_3$	$w_2$	0	0	$w_3$	0

(Case B)

$$\begin{split} \psi_{\{1\}} + \psi_{\{1,2\}} + \psi_{\{2\}} &= H\left(U_{1,2}, U_{2,2}\right), \\ \psi_{\{1\}} + \psi_{\{1,3\}} + \psi_{\{3\}} &= H\left(U_{1,2}, U_{3,2}\right), \\ \psi_{\{2\}} + \psi_{\{2,3\}} + \psi_{\{3\}} &= H\left(U_{2,2}|U_{1,2}\right) + H\left(U_{3,2}|U_{1,2}\right) \\ &> H\left(U_{2,2}, U_{3,2}\right); \end{split}$$

(Case C)

$$\begin{split} \psi_{\{1\}} + \psi_{\{1,2\}} + \psi_{\{2\}} &= H\left(U_{1,2}, U_{2,2}\right), \\ \psi_{\{1\}} + \psi_{\{1,3\}} + \psi_{\{3\}} &= H\left(U_{1,2}|U_{2,2}\right) + H\left(U_{3,2}|U_{2,2}\right) \\ &> H\left(U_{1,2}, U_{3,2}\right), \\ \psi_{\{2\}} + \psi_{\{2,3\}} + \psi_{\{3\}} &= H\left(U_{2,2}, U_{3,2}\right); \end{split}$$

(Case D)

$$\begin{split} \psi_{\{1\}} + \psi_{\{1,2\}} + \psi_{\{2\}} &= H\left(U_{1,2}|U_{3,2}\right) + H\left(U_{2,2}|U_{3,2}\right) \\ &> H\left(U_{1,2}, U_{2,2}\right), \\ \psi_{\{1\}} + \psi_{\{1,3\}} + \psi_{\{3\}} &= H\left(U_{1,2}, U_{3,2}\right), \\ \psi_{\{2\}} + \psi_{\{2,3\}} + \psi_{\{3\}} &= H\left(U_{2,2}, U_{3,2}\right). \end{split}$$

Now one can readily solve  $LP_{3,2}^{\mathbf{w}}$  with  $\mathbf{w} \in \mathbb{W}_3$  by considering all possible combinations of these four cases and those in Table I (i.e., Cases 1–5). For example, consider the scenario where Case 2 and Case C are simultaneously satisfied (henceforth called Case 2C). It can be verified that

$$\begin{split} \psi_{\{1\}} &= H\left(U_{1,2}|U_{2,2}\right),\\ \psi_{\{3\}} &= H\left(U_{3,2}|U_{2,2}\right),\\ \psi_{\{1,3\}} &= 0,\\ \psi_{\{1\}} + \psi_{\{1,2\}} + \psi_{\{2\}} &= H\left(U_{1,2}, U_{2,2}\right). \end{split}$$

For  $\left(\tilde{r}_{k,2}^{\text{opt}}, k \in [1:3]\right)$  in Table I, we have

$$\begin{split} \tilde{r}_{1,2}^{\text{opt}} &= \psi_{\{1\}} + \psi_{\{1,3\}} \\ &= H\left(U_{1,2}|U_{2,2}\right), \\ \tilde{r}_{2,2}^{\text{opt}} &= \psi_{\{2\}} + \psi_{\{1,2\}} - \psi_{\{1,3\}} \\ &= \left(\psi_{\{1\}} + \psi_{\{1,2\}} + \psi_{\{2\}}\right) - \left(\psi_{\{1\}} + \psi_{\{1,3\}}\right) \\ &= H\left(U_{2,2}\right), \end{split}$$

$$\tilde{r}_{3,2}^{\text{opt}} = \psi_{\{3\}} = H \left( U_{3,2} | U_{2,2} \right)$$

In view of Lemma 5,  $(r_{k,2}^{\text{opt}}, k \in [1:K])$  with  $r_{k,2}^{\text{opt}} \triangleq \tilde{r}_{k,2}^{\text{opt}}$ ,  $k \in [1:K]$ , is an optimal solution of  $\mathsf{LP}_{3,2}^{\mathsf{w}}$ . Therefore, the optimal value of  $\mathsf{LP}_{3,2}^{\mathsf{w}}$  is given by

$$f_2^{\mathbf{w}} = w_1 H \left( U_{1,2} | U_{2,2} \right) + w_2 H \left( U_{2,2} \right) + w_3 H \left( U_{3,2} | U_{2,2} \right).$$

Moreover,  $(c_{V|V',2}, V \in \mathbb{V}_{3,2}, V' \in \mathbb{V}'_{3,2}[V])$  with

$$c_{\{1\}|\{2\},2} \triangleq w_1 - w_2, \\c_{\{3\}|\{2\},2} \triangleq w_3, \\c_{\{1,2\}|\emptyset,2} \triangleq w_2, \\c_{V|V',2} \triangleq 0, \text{ otherwise}$$

is an optimal Lagrange multiplier of  $LP_{3,2}^{w}$ .

One can obtain the following lemma by analyzing the other combinations in the same manner. It is worth mentioning that not all combinations are possible. Specifically, Cases 2D, 3C, and 4B violate Lemma 6(2), so such combinations are void.

*Lemma 7:* For linear program  $LP_{3,2}^{\mathbf{w}}$  with  $\mathbf{w} \in W_3$ ,  $(c_{V|V',2}, V \in \mathbb{V}_{3,2}, V' \in \mathbb{V}'_{3,2}[V])$  in Table II<sup>5</sup> is an optimal Lagrange multiplier. The general case  $\mathbf{w} \in \mathbb{R}^3_+$  can be reduced to the case  $\mathbf{w} \in \mathbb{W}_3$  via suitable relabelling.

The next result shows that (6) holds when K = 3, which, together with (3) and Lemma 4, completes the proof of Theorem 1.

Lemma 8: We have

$$\sum_{V \in \mathbb{V}_{3,1}} c_{V,1} H(X_V) \ge \sum_{V \in \mathbb{V}_{3,2}} \sum_{V' \in \mathbb{V}'_{3,2}[V]} c_{V|V',2} H(X_V|X_{V'})$$

$$\ge \sum_{V \in \mathbb{V}_{3,3}} c_{V,3} H(X_V|X_{[1:3]\setminus V})$$
(21)
(22)

for all  $X_{[1:3]}$ , where  $(c_{V,1}, V \in \mathbb{V}_{3,1})$ ,  $(c_{V|V',2}, V \in \mathbb{V}_{3,2}, V' \in \mathbb{V}'_{3,2}[V])$ , and  $(c_{V,3}, V \in \mathbb{V}_{3,3})$  are the optimal Lagrange multipliers in Lemma 1, Lemma 2, and Lemma 7, respectively.

<sup>5</sup>We set  $c_{\{k\}|\{k'\},2} = 0$  for  $k' \neq v_k$ .

*Proof:* Note that (21) follows from Lemma 3. The proof of (22) is relegated to Appendix B.  $\blacksquare$ 

### V. PROOF OF THEOREM 2

The proof of Theorem 2 also largely follows the general approach outlined in Section III. However, due to the symmetry assumption, some simplifications are possible.

## A. Linear Program

When the distribution of  $U_{[1:K],[1:K]}$  is symmetrical entropy-wise,  $H(U_{V,\alpha}|U_{V',\alpha})$  depends on  $V \in \mathbb{V}_{K,\alpha}$  and  $V' \in \mathbb{V}'_{K,\alpha}[V]$  only through |V|; for this reason, we shall denote it as  $H_{|V|,\alpha}$  and rewrite  $\mathsf{LP}^{\mathbf{w}}_{K,\alpha}$  in the following simpler form

$$\overline{\mathsf{LP}}_{K,\alpha}^{\mathbf{w}}: \min \sum_{k=1}^{K} w_k r_{k,\alpha}$$
  
over  $r_{k,\alpha}, \quad k \in [1:K],$   
s.t.  $\sum_{k \in V} r_{k,\alpha} \ge H_{|V|,\alpha}, \quad V \in \mathbb{V}_{K,\alpha}.$ 

Definition 3: We say that  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha})$  is an optimal Lagrange multiplier of  $\overline{\mathsf{LP}}_{K,\alpha}^{\mathbf{w}}$  with  $\mathbf{w} \in \mathbb{R}_{+}^{K}$  if

$$\sum_{V \in \mathbb{V}_{K,\alpha}} c_{V,\alpha} H_{|V|,\alpha} = \overline{f}_{\alpha}^{\mathbf{w}}, \tag{23}$$

$$\sum_{V \in \mathbb{V}_{K,\alpha}: k \in V} c_{V,\alpha} = w_k, \quad k \in [1:K],$$
(24)

$$c_{V,\alpha} \ge 0, \quad V \in \mathbb{V}_{K,\alpha},$$
 (25)

where  $\overline{f}_{\alpha}^{\mathbf{w}}$  denotes the optimal value of  $\overline{\mathsf{LP}}_{K,\alpha}^{\mathbf{w}}$ . For  $l \in [0 : \alpha - 1]$ , define

$$r_{k,\alpha}^{(l)} \triangleq \begin{cases} H_{k,\alpha} - H_{k-1,\alpha}, & k \in [1:l], \\ \frac{H_{\alpha,\alpha} - H_{l,\alpha}}{\alpha - l}, & k \in [l+1:K], \end{cases}$$

where  $H_{0,\alpha} \triangleq 0$ .

Lemma 9: 
$$(r_{k,\alpha}^{(l)}, k \in [1:K]) \in \mathcal{R}_{K,\alpha}$$
.  
*Proof:* See Appendix C.  
For  $\alpha \in [1:K]$  and  $l \in [0:\alpha - 1]$ , define

$$\Omega_{K,\alpha}^{(l)} \triangleq \{V \subseteq [1:K] : |V| = \alpha, [1:l] \subseteq V\}.$$

Recall that  $\mathbb{W}_{K,\alpha}^{(0)}, \cdots, \mathbb{W}_{K,\alpha}^{(\alpha-1)}$  form a partition of  $\mathbb{W}_K$ . For  $\mathbf{w} \in \mathbb{W}_K$  and  $\alpha \in [1:K]$ , let  $l_{\alpha}^{\mathbf{w}}$  denote the unique integer in  $[0:\alpha-1]$  such that  $\mathbf{w} \in \mathbb{W}_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}$ ; it is easy to verify that

$$0 = l_1^{\mathbf{w}} \le l_2^{\mathbf{w}} \le \dots \le l_{K-1}^{\mathbf{w}} \le l_K^{\mathbf{w}}.$$

Moreover, for  $\mathbf{w} \in \mathbb{W}_K$  and  $\alpha \in [1:K]$ , define

$$\lambda_{\alpha}^{\mathbf{w}} \triangleq \frac{1}{\alpha - l_{\alpha}^{\mathbf{w}}} \sum_{k=l_{\alpha}^{\mathbf{w}}+1}^{K} w_{k}$$

and

$$\mathbb{C}_{K,\alpha}^{\mathbf{w}} \triangleq \left\{ \left( c_{V,\alpha} : V \in \mathbb{V}_{K,\alpha} \right) : \\ c_{[1:k],\alpha} = w_k - w_{k+1}, \quad k \in [1:l_{\alpha}^{\mathbf{w}} - 1], \quad (26) \right\}$$

$$c_{\left[1:l_{\alpha}^{\mathbf{w}}\right],\alpha} = w_{l_{\alpha}^{\mathbf{w}}} - \lambda_{\alpha}^{\mathbf{w}},\tag{27}$$

$$c_{V,\alpha} \ge 0, \quad V \in \Omega_{K,\alpha}^{(l_{\alpha}^{-})},$$
(28)

(1W)

$$c_{V,\alpha} = 0$$
, otherwise, (29)

$$\sum_{\substack{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{W}})}: k \in V}} c_{V,\alpha} = w_k, \quad k \in \left[ l_{\alpha}^{\mathbf{W}} + 1 : K \right] \bigg\}.$$
(30)

Note that (26) and (27) are void when  $l_{\alpha}^{\mathbf{w}} = 0$ . The definition of  $\mathbb{C}_{K,\alpha}^{\mathbf{w}}$  can be extended to the case  $\mathbf{w} \in \mathbb{R}_{+}^{K}$  through suitable relabelling.

Lemma 10: For any  $\mathbf{w} \in \mathbb{W}_K$ ,  $(c_{V,\alpha-1}, V \in \mathbb{V}_{K,\alpha-1}) \in \mathbb{C}_{K,\alpha-1}^{\mathbf{w}}$ , and  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}) \in \mathbb{C}_{K,\alpha}^{\mathbf{w}}$ ,

$$\sum_{\substack{V \in \Omega_{\nu_{\alpha}}^{(\mathsf{W})}}} c_{V,\alpha} = \lambda_{\alpha}^{\mathsf{W}},\tag{31}$$

$$\sum_{i:\mathbb{V}_{K,\alpha}:k\in V} c_{V,\alpha} = w_k, \quad k \in [1:K],$$
(32)

$$c_{V,\alpha} \ge 0, \quad V \in \mathbb{V}_{K,\alpha}, \tag{33}$$

$$c_{[1:l_{\alpha-1}^{\mathbf{w}}],\alpha} - c_{[1:l_{\alpha-1}^{\mathbf{w}}],\alpha-1} = \theta_{\alpha}^{\mathbf{w}} \ge 0,$$
(34)

$$\sum_{V \in \mathbb{V}_{K,a}} c_{V,a} = \begin{cases} \frac{1}{\alpha} \sum_{k=1}^{\infty} w_k, & l_a^{\mathbf{w}} = 0, \\ w_1, & l_a^{\mathbf{w}} > 0, \end{cases}$$
(35)

where

 $V \in$ 

$$\theta_{\alpha}^{\mathbf{w}} \triangleq \left(\lambda_{\alpha}^{\mathbf{w}} - \sum_{k=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} \left(\alpha - 1 - k\right) c_{[1:k],\alpha}\right) \frac{1}{\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}}.$$
(36)

Proof: See Appendix D.

The main result of Section V-A is as follows. Lemma 11: For linear program  $\overline{\mathsf{LP}}_{K,\alpha}^{\mathbf{w}}$  with  $\mathbf{w} \in \mathbb{W}_K$ ,  $\begin{pmatrix} r_{k,\alpha}^{(l_{\alpha}^u)}, k \in [1:K] \end{pmatrix}$  is an optimal solution, and every  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}) \in \mathbb{C}_{K,\alpha}^{\mathbf{w}}$  is an optimal Lagrange multiplier. *Proof:* In view of Lemma 9, we have  $\begin{pmatrix} r_{k,\alpha}^{(l_{\alpha}^w)}, k \in [1:K] \end{pmatrix} \in \mathcal{R}_{K,\alpha}$ . Consider an arbitrary  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}) \in \mathbb{C}_{K,\alpha}^{\mathbf{w}}$ . It follows from Lemma 10 that  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha})$  satisfies (24) and (25). Note that

$$\sum_{k=1}^{K} w_k r_{k,a}^{(l_{\alpha}^{\mathbf{w}})}$$

$$= \sum_{k=1}^{l_{\alpha}^{\mathbf{w}}} w_k \left(H_{k,a} - H_{k-1,a}\right) + \sum_{k=l_{\alpha}^{\mathbf{w}}+1}^{K} w_k \frac{H_{\alpha,a} - H_{l_{\alpha}^{\mathbf{w}},a}}{\alpha - l_{\alpha}^{\mathbf{w}}}$$

$$= \sum_{k=1}^{l_{\alpha}^{\mathbf{w}}-1} \left(w_k - w_{k+1}\right) H_{k,a} + \left(w_{l_{\alpha}^{\mathbf{w}}} - \lambda_{\alpha}^{\mathbf{w}}\right) H_{l_{\alpha}^{\mathbf{w}},a} + \lambda_{\alpha}^{\mathbf{w}} H_{\alpha,a}$$

$$= \sum_{k=1}^{l_{\alpha}^{\mathbf{w}}-1} c_{[1:k],\alpha} H_{k,\alpha} + c_{[1:l_{\alpha}^{\mathbf{w}}],\alpha} H_{l_{\alpha}^{\mathbf{w}},a} + \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,\alpha} H_{\alpha,\alpha} \quad (37)$$

$$= \sum_{V \in \mathbb{V}_{K,\alpha}} c_{V,\alpha} H_{|V|,\alpha},$$

where (37) is due to (31). On the other hand, for any  $(r_{k,\alpha} : k \in [1:K]) \in \mathcal{R}_{K,\alpha}$ ,

$$\sum_{k=1}^{K} w_k r_{k,\alpha} = \sum_{k=1}^{K} \sum_{V \in \mathbb{V}_{K,\alpha} : k \in V} c_{V,\alpha} r_{k,\alpha}$$
$$= \sum_{V \in \mathbb{V}_{K,\alpha}} c_{V,\alpha} \sum_{k \in V} r_{k,\alpha}$$
$$\ge \sum_{V \in \mathbb{V}_{K,\alpha}} c_{V,\alpha} H_{|V|,\alpha}.$$

Therefore,  $\left(r_{k,\alpha}^{(l_{\alpha}^{W})}, k \in [1:K]\right)$  is an optimal solution. This also shows that  $\left(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}\right)$  satisfies (23), thus is indeed an optimal Lagrange multiplier.

#### B. Entropy Inequality

Define the indicator function

$$\mathcal{I} \text{ (event)} \triangleq \begin{cases} 1, & \text{event is true,} \\ 0, & \text{event is false.} \end{cases}$$

*Lemma 12:* For  $\mathbf{w} \in \mathbb{W}_K$  with  $\lambda_{\alpha}^{\mathbf{w}} > 0$  and  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}) \in \mathbb{C}_{K,\alpha}^{\mathbf{w}}$ , define  $(c_{V',\alpha-1}, V' \in \mathbb{V}_{K,\alpha-1})$  as follows:

$$c_{[1:k]\alpha-1} \triangleq w_{k} - w_{k+1}, \quad k \in [1:l_{\alpha-1}^{\mathbf{w}} - 1],$$

$$c_{[1:l_{\alpha-1}^{\mathbf{w}}]\alpha-1} \triangleq w_{l_{\alpha-1}^{\mathbf{w}}} - \lambda_{\alpha-1}^{\mathbf{w}},$$

$$c_{V',\alpha-1} \triangleq \frac{\theta_{\alpha}^{\mathbf{w}}}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}: V' \subseteq V} c_{V,\alpha} + \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,\alpha}$$

$$\times \sum_{k=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} c_{[1:k]\alpha} \sum_{\tau=k+1}^{\alpha} \mathcal{I} \{V' = \langle V \rangle_{[1:\alpha] \setminus \{\tau\}} \},$$

$$V' \in \Omega_{K,\alpha-1}^{(l_{\alpha-1}^{\mathbf{w}})},$$

 $c_{V',\alpha-1} \triangleq 0$ , otherwise,

where  $\theta_{\alpha}^{\mathbf{w}}$  is given by (36). The following statements are true. (1)  $(c_{V',\alpha-1}, V' \in \mathbb{V}_{K,\alpha-1}) \in \mathbb{C}_{K,\alpha-1}^{\mathbf{w}}$ .

(2) We have

$$\sum_{V'\in\mathbb{V}_{K,\alpha-1}}c_{V',\alpha-1}H\left(X_{V'}\right)\geq\sum_{V\in\mathbb{V}_{K,\alpha}}c_{V,\alpha}H\left(X_{V}\right)$$

for all  $X_{[1:K]}$ .

Proof: See Appendix E.

*Lemma 13:* Given any  $\mathbf{w} \in \mathbb{R}_{+}^{K}$ , there exist  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}) \in \mathbb{C}_{K,\alpha}^{\mathbf{w}}, \alpha \in [1:K]$ , such that

$$\sum_{V' \in \mathbb{V}_{K,\alpha'}} c_{V',\alpha'} H\left(X_{V'}\right) \ge \sum_{V \in \mathbb{V}_{K,\alpha}} c_{V,\alpha} H\left(X_{V}\right)$$
(38)

for all  $X_{[1:K]}$  and  $\alpha \ge \alpha'$ .

*Proof:* By symmetry, it suffices to consider  $\mathbf{w} \in \mathbb{W}_K$ . We shall first assume  $w_K > 0$ , which implies  $\lambda_{\alpha}^{\mathbf{w}} > 0$ ,  $\alpha \in [1 : K]$ . Define  $(c_{V,K}, V \in \mathbb{V}_{K,K})$  with

$$c_{[1:k],K} \triangleq w_k - w_{k+1}, \quad k \in [1:K],$$
  
$$c_{V,K} \triangleq 0, \quad \text{otherwise.}$$

It is easy to verify that  $(c_{V,K}, V \in \mathbb{V}_{K,K}) \in \mathbb{C}_{K,K}^{\mathbf{w}}$ . One can successively construct the desired  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha})$  from  $\alpha = K - 1$  to  $\alpha = 1$  by invoking Lemma 12.

Now consider the case  $w_1 \ge \cdots \ge w_{K-1} > w_K = 0$ . The preceding argument implies the existence of  $(c'_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}) \in \mathbb{C}^{\mathbf{w}'}_{K-1,\alpha}, \alpha \in [1:K-1]$ , such that

$$\sum_{\substack{i' \in \mathbb{V}_{K-1,\alpha'}}} c'_{V',\alpha'} H\left(X_{V'}\right) \ge \sum_{V \in \mathbb{V}_{K-1,\alpha}} c'_{V,\alpha} H\left(X_{V}\right)$$

for all  $X_{[1:K-1]}$  and  $\alpha \geq \alpha'$ , where  $\mathbf{w}' \triangleq (w_1, \cdots, w_{K-1})$ . Define  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}), \alpha \in [1:K-1]$ , with

$$c_{V,\alpha} \triangleq c'_{V,\alpha}, \quad K \notin V,$$
  
 $c_{V,\alpha} \triangleq 0, \quad \text{otherwise,}$ 

and  $(c_{V,K}, V \in \mathbb{V}_{K,K})$  with

V

$$c_{V,K} \triangleq c'_{V,K-1}, \quad K \notin V,$$
  
 $c_{V,K} \triangleq 0, \quad \text{otherwise.}$ 

It is easy to verify that such  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}), \alpha \in [1:K]$ , have the desired properties. The general case where  $w_1 \ge \cdots \ge w_{K'-1} > w_{K'} = \cdots = w_K = 0$  for some  $K' \le K$ can be handled via induction.<sup>6</sup>

#### C. Outer Bound

The following result, together with (3) and Lemma 13, completes the proof of Theorem 2.

*Lemma 14:* If given any  $\mathbf{w} \in \mathbb{R}_{+}^{K}$ , there exist  $(c_{V,\alpha}, V \in \mathbb{V}_{K,\alpha}) \in \mathbb{C}_{K,\alpha}^{\mathbf{w}}, \alpha \in [1:K]$ , such that (38) holds, then

$$\mathcal{R}_K^* \subseteq \mathcal{R}_K$$

when the distribution of  $U_{[1:K][1:K]}$  is symmetrical entropy-wise.

*Proof:* Let  $(R_k : k \in [1 : K])$  be an arbitrary admissible rate tuple. It suffices to show that

$$\sum_{k=1}^{K} w_k R_k \ge \sum_{\alpha=1}^{K} \overline{f}_{\alpha}^{\mathbf{w}}.$$
(39)

Without loss of generality, we assume  $\mathbf{w} \in \mathbb{W}_K$ . We shall prove via induction that, when the distribution of  $U_{[1:K][1:K]}$  is symmetrical entropy-wise, for any D-MLDC system satisfying (1) and (2),

$$\sum_{k=1}^{K} w_k \left( R_k + \epsilon \right)$$

$$\geq \sum_{\alpha=1}^{\beta} \overline{f}_{\alpha}^{\mathbf{w}} + \frac{1}{n} \sum_{k=1}^{l_{\beta}^{\mathbf{w}}} c_{[1:k]\beta} H \left( S_{[1:k]} | U_{[1:K][1:\beta]}^n, U_{[k+1:\beta]K}^n \right)$$

$$+ \frac{1}{n} \sum_{V \in \Omega_{K,\beta}^{(l_{\beta}^{\mathbf{w}})}} c_{V,\beta} H \left( S_V | U_{[1:K][1:\beta]}^n \right) - \beta \delta_{\epsilon} \sum_{k=1}^{K} w_k,$$

$$\beta \in [1:K], \qquad (40)$$

<sup>6</sup>If  $w_1 = \cdots = w_K = 0$ , then  $c_{V,\alpha} = 0$  for all  $V \in \mathbb{V}_{K,\alpha}$  and  $\alpha \in [1:K]$ .

where  $\delta_{\epsilon}$  tends to zero as  $\epsilon \to 0$ . One can deduce (39) from (40) by setting  $\beta = K$  and sending  $\epsilon \to 0$ .

The proof of (40) for  $\beta = 1$  is the same as that of (11). Now assume that (40) holds for  $\beta = B - 1$ . In view of (38), we have

$$\sum_{\substack{V' \in \Omega_{K,B-1}^{(l_{B-1}^{w})}} c_{V',B-1}H\left(S_{V'}|U_{[1:K],[1:B-1]}^{n}\right)$$

$$\geq \sum_{\substack{k=1\\k=1}}^{l_{B}^{w}} \left(c_{[1:k],B} - c_{[1:k],B-1}\mathcal{I}\left\{k \leq l_{B-1}^{w}\right\}\right)$$

$$\times H\left(S_{[1:k]}|U_{[1:K],[1:B-1]}^{n}\right)$$

$$+ \sum_{\substack{V \in \Omega_{K,B}^{(l_{B}^{w})}} c_{V,B}H\left(S_{V}|U_{[1:K],[1:B-1]}^{n}\right), \quad (41)$$

where  $c_{[1:k]B} - c_{[1:k]B-1}\mathcal{I}\{k \le l_{B-1}^{w}\} \ge 0, k \in [1:l_{B}^{w}],$ according to (33), (34), and the fact that  $c_{[1:k]B-1} = c_{[1:k]B}$ when  $k \in [1:l_{B-1}^{w} - 1]$ . Moreover,

$$\sum_{k=1}^{l_{B}^{w}} \left( c_{[1:k]B} - c_{[1:k]B-1}\mathcal{I}\left\{k \leq l_{B-1}^{w}\right\} \right) \\ \times H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}\right) \\ \geq \sum_{k=1}^{l_{B}^{w}} \left( c_{[1:k]B} - c_{[1:k]B-1}\mathcal{I}\left\{k \leq l_{B-1}^{w}\right\} \right) \\ \times H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ = \sum_{k=1}^{l_{B}^{w}} c_{[1:k]B}H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ - \sum_{k=1}^{l_{B}^{w-1}} c_{[1:k]B-1}H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ \geq \sum_{k=1}^{l_{B}^{w}} c_{[1:k]B}H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ - \sum_{k=1}^{l_{B}^{w-1}} c_{[1:k]B-1}H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ + H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}, U_{[k+1:B-1][B-1:K]}^{n}\right).$$
(42)

Combining (41) and (42) gives

$$\sum_{k=1}^{l_{B-1}^{w}} c_{[1:k]B-1}H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}, U_{[k+1:B-1][B-1:K]}^{n}\right) \\ + \sum_{V'\in\Omega_{K,B-1}^{(l_{B-1}^{w})}} c_{V',B-1}H\left(S_{V'}|U_{[1:K][1:B-1]}^{n}\right) \\ \ge \sum_{k=1}^{l_{B}^{w}} c_{[1:k]B}H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ + \sum_{V\in\Omega_{K,B}^{(l_{B}^{w})}} c_{V,B}H\left(S_{V}|U_{[1:K][1:B-1]}^{n}\right).$$
(43)

Note that

$$\begin{split} H\left(S_{[1:k]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ &= H\left(S_{[1:k]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}, S_{[k+1:B]}\right) \\ &= H\left(S_{[1:B]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}, S_{[k+1:B]}\right) \\ &= H\left(U_{[1:B],[1:B]}^{n}, S_{[1:B]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}, S_{[k+1:B]}\right) \\ &- H\left(U_{[1:B],[1:B]}^{n}, S_{[1:B]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}, S_{[1:B]}\right) \\ &\geq H\left(U_{[1:B],[1:B]}^{n}, S_{[1:B]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}, S_{[1:B]}\right) \\ &\geq H\left(U_{[1:B],[1:B]}^{n}, S_{[1:B]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}, S_{[k+1:B]}\right) \\ &+ H\left(U_{[1:B],[1:B]}^{n}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}, S_{[k+1:B]}\right) \\ &+ H\left(S_{[1:B]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ &+ H\left(S_{[1:B]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ &+ H\left(S_{[1:k]}|U_{[1:K],[1:B-1]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ &- n\delta_{\epsilon} \\ &\geq nH_{k,B} + H\left(S_{[1:k]}|U_{[1:K],[1:B]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) - n\delta_{\epsilon}, \\ &k \in \left[1:l_{B}^{m}\right], \tag{45} \end{split}$$

where (44) follows by (2) and Fano's inequality. Similarly, we have

$$H\left(S_{V}|U_{[1:K][1:B-1]}^{n}\right) = H\left(U_{V,[1:B]}^{n}, S_{V}|U_{[1:K][1:B-1]}^{n}\right) \\ -H\left(U_{V,[1:a]}^{n}|U_{[1:K][1:B-1]}^{n}, S_{V}\right) \\ \ge H\left(U_{V,[1:B]}^{n}, S_{V}|U_{[1:K][1:B-1]}^{n}\right) - n\delta_{\epsilon} \\ = H\left(U_{V,[1:B]}^{n}|U_{[1:K][1:B-1]}^{n}\right) \\ +H\left(S_{V}|U_{[1:K][1:B-1]}^{n}, U_{V,[1:B]}^{n}\right) - n\delta_{\epsilon} \\ \ge nH_{|V|,B} + H\left(S_{V}|U_{[1:K][1:B]}^{n}\right) - n\delta_{\epsilon}, \quad V \in \Omega_{K,B}^{(l_{B}^{w})}.$$

$$(46)$$

Continuing from (43),

$$\sum_{k=1}^{l_{B-1}^{w}} c_{[1:k]B-1}H\left(S_{[1:k]}|U_{[1:K][1:B-1]}^{n}, U_{[k+1:B-1][B-1:K]}^{n}\right) \\ + \sum_{V' \in \Omega_{K,B-1}^{\left(l_{B-1}^{w}\right)}} c_{V',B-1}H\left(S_{V'}|U_{[1:K][1:B-1]}^{n}\right) \\ \ge n \sum_{V \in \mathbb{V}_{K,B}} c_{V,B}H_{|V|,B} \\ + \sum_{k=1}^{l_{B}^{w}} c_{[1:k]B} \cdot H\left(S_{[1:k]}|U_{[1:K][1:B]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) \\ + \sum_{V \in \Omega_{K,B}^{\left(l_{B}^{w}\right)}} c_{V,B}H\left(S_{V}|U_{[1:K][1:B]}^{n}\right) - n\delta_{\epsilon} \sum_{V \in \mathbb{V}_{K,B}} c_{V,B} \\ \le n \overline{t}_{\infty}^{w}$$

$$(47)$$

$$\geq n\overline{f}_{B}^{w} + \sum_{k=1}^{l_{B}^{w}} c_{[1:k],B} \cdot H\left(S_{[1:k]}|U_{[1:K],[1:B]}^{n}, U_{[k+1:B],[B:K]}^{n}\right) + \sum_{V \in \Omega_{K,B}^{(W)}} c_{V,B}H\left(S_{V}|U_{[1:K],[1:B]}^{n}\right) - n\delta_{\epsilon} \sum_{k=1}^{K} w_{k}, \quad (48)$$

where (47) is due to (45) and (46), and (48) is due to (23), (35) as well as Lemma 11. Combining (48) and the induction hypothesis proves (40) for  $\beta = B$ .

# VI. CONCLUSION

We have characterized the admissible rate region of D-MLDC for the case  $K \leq 3$  and the case where the source distribution is symmetrical entropy-wise. In view of the intimate connection between MLDC and its lossy counterpart known as multiple description coding [14], it is expected that the results in the present work may shed new light on the robust distributed source coding problem (which is the lossy counterpart of D-MLDC) studied in [15].

## APPENDIX A Proof of Lemma 6

*Proof of Part (1) of Lemma 6:* It follows by the definition of  $\psi_{\{i,j\}}$  that

$$\psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}} = H(U_{i,2}, U_{j,2})$$

when  $H(U_{i,2}, U_{j,2}) \ge \psi_{\{i\}} + \psi_{\{j\}}$ . When  $H(U_{i,2}, U_{j,2}) < \psi_{\{i\}} + \psi_{\{j\}}$ , we must have

$$\psi_{\{i\}} = H(U_{i,2}|U_{k,2}), \\ \psi_{\{j\}} = H(U_{j,2}|U_{k,2}), \\ \psi_{\{i,j\}} = 0,$$

and consequently

$$\psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}} = H\left(U_{i,2}|U_{k,2}\right) + H\left(U_{j,2}|U_{k,2}\right)$$

*Proof of Part (2) of Lemma 6:* Note that  $\psi_{\{i,j\}} > \psi_{\{i,k\}} + \psi_{\{j,k\}}$  implies  $\psi_{\{i,j\}} > 0$ . It then follows by the definition of  $\psi_{\{i,j\}}$  that

$$\psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}} = H(U_{i,2}, U_{j,2})$$

Proof of Part (3) of Lemma 6: In view of the fact that  $\psi_{\{i\}} \ge H(U_{i,2}|U_{k,2}), \ \psi_{\{j\}} \ge H(U_{j,2}|U_{k,2}), \text{ and } \psi_{\{i,j\}} \ge 0,$  we must have

$$\begin{aligned}
\psi_{\{i\}} &= H\left(U_{i,2}|U_{k,2}\right), \\
\psi_{\{j\}} &= H\left(U_{j,2}|U_{k,2}\right), \\
\psi_{\{i,j\}} &= 0
\end{aligned} \tag{49}$$

when  $\psi_{\{i\}} + \psi_{\{i,j\}} + \psi_{\{j\}} = H(U_{i,2}|U_{k,2}) + H(U_{j,2}|U_{k,2}).$ Note that

$$H(U_{i,2}, U_{k,2}) = H(U_{i,2}|U_{k,2}) + H(U_{k,2})$$
  
=  $\psi_{\{i\}} + H(U_{k,2})$   
 $\geq \psi_{\{i\}} + \psi_{\{k\}},$  (50)

where (50) is due to (49). It follows by symmetry that  $H(U_{j,2}, U_{k,2}) \ge \psi_{\{j\}} + \psi_{\{k\}}$ . Invoking the definition of  $\psi_{\{i,k\}}$  and  $\psi_{\{j,k\}}$  completes the proof of Lemma 6.

## APPENDIX B Proof of (22) in Lemma 8

It suffices to consider  $\mathbf{w} \in \mathbb{W}_3$ . Case 1A ( $\mathbf{w} \in \mathbb{W}_{3,2}^{(0)}$ ):

$$\frac{1}{2} (w_{1} + w_{2} - w_{3}) H (X_{1}, X_{2}) + \frac{1}{2} (w_{1} - w_{2} + w_{3}) H (X_{1}, X_{3}) + \frac{1}{2} (-w_{1} + w_{2} + w_{3}) H (X_{2}, X_{3}) = (w_{1} - w_{2}) (H (X_{1}, X_{2}) + H (X_{1}, X_{3}) -H (X_{1}, X_{2}, X_{3})) + (w_{2} - w_{3}) H (X_{1}, X_{2}) + \frac{1}{2} (-w_{1} + w_{2} + w_{3}) \times (H (X_{1}, X_{2}) + H (X_{1}, X_{3}) + H (X_{2}, X_{3})) + (w_{1} - w_{2}) H (X_{1}) + (w_{2} - w_{3}) H (X_{1}, X_{2}) + \frac{1}{2} (-w_{1} + w_{2} + w_{3}) \times (H (X_{1}, X_{2}) + H (X_{1}, X_{3}) + H (X_{2}, X_{3})) + (w_{1} - w_{2}) H (X_{1}) + (w_{2} - w_{3}) H (X_{2}, X_{3})) + (w_{1} - w_{2}) H (X_{1}, X_{2}, X_{3}) \geq (w_{1} - w_{2}) H (X_{1}) + (w_{2} - w_{3}) H (X_{1}, X_{2}) + w_{3} H (X_{1}, X_{2}, X_{3})$$
(51)  
$$\geq (w_{1} - w_{2}) H (X_{1} | X_{2}, X_{3}) + (w_{2} - w_{3}) H (X_{1}, X_{2} | X_{3}) + w_{3} H (X_{1}, X_{2}, X_{3}),$$

where (51) is due to Han's inequality [16]. Case 1B ( $\mathbf{w} \in \mathbb{W}_{3,2}^{(0)}$  and  $\nu_2 = \nu_3 = 1$ ):

$$\begin{aligned} \frac{1}{2} \left(-w_1 + w_2 + w_3\right) \left(H\left(X_2|X_1\right) + H\left(X_3|X_1\right)\right) \\ &+ \frac{1}{2} \left(w_1 + w_2 - w_3\right) H\left(X_1, X_2\right) \\ &+ \frac{1}{2} \left(w_1 - w_2 + w_3\right) H\left(X_1, X_3\right) \\ \geq \frac{1}{2} \left(-w_1 + w_2 + w_3\right) \left(H\left(X_2|X_1, X_3\right) + H\left(X_3|X_1, X_2\right)\right) \\ &+ \frac{1}{2} \left(w_1 + w_2 - w_3\right) H\left(X_1, X_2\right) \\ &+ \frac{1}{2} \left(w_1 - w_2 + w_3\right) H\left(X_1, X_3\right) \\ = \left(w_1 - w_2\right) \left(H\left(X_1, X_2\right) + H\left(X_1, X_3\right) \\ &- H\left(X_1, X_2, X_3\right)\right) + \left(w_2 - w_3\right) H\left(X_1, X_2\right) \\ &+ \frac{1}{2} \left(-w_1 + w_2 + w_3\right) \left(H\left(X_3|X_1, X_2\right) + H\left(X_1, X_2\right)\right) \\ &+ \frac{1}{2} \left(-w_1 + w_2 + w_3\right) \left(H\left(X_2|X_1, X_3\right) + H\left(X_1, X_3\right)\right) \\ &+ \left(w_1 - w_2\right) H\left(X_1, X_2, X_3\right) \\ \geq \left(w_1 - w_2\right) H\left(X_1\right) + \left(w_2 - w_3\right) H\left(X_1, X_2\right) \\ &+ w_3 H\left(X_1, X_2, X_3\right) \\ \geq \left(w_1 - w_2\right) H\left(X_1|X_2, X_3\right) + \left(w_2 - w_3\right) H\left(X_1, X_2|X_3\right) \\ &+ w_3 H\left(X_1, X_2, X_3\right). \end{aligned}$$

Case 1C (
$$v_1 = v_3 = 2$$
):  

$$\frac{1}{2}(w_1 - w_2 + w_3)(H(X_1|X_2) + H(X_3|X_2)) + \frac{1}{2}(w_1 + w_2 - w_3)H(X_1, X_2) + \frac{1}{2}(-w_1 + w_2 + w_3)H(X_2, X_3) + H(X_3|X_1, X_2)) + \frac{1}{2}(w_1 - w_2 + w_3)(H(X_1|X_2, X_3) + H(X_3|X_1, X_2)) + \frac{1}{2}(-w_1 + w_2 + w_3)H(X_2, X_3) = (w_1 - w_2)H(X_1|X_2, X_3) + (w_2 - w_3)H(X_1, X_2) + \frac{1}{2}(-w_1 + w_2 + w_3)(H(X_1|X_2, X_3) + H(X_2, X_3)) + \frac{1}{2}(w_1 - w_2 + w_3)(H(X_3|X_1, X_2) + H(X_1, X_2)) = (w_1 - w_2)H(X_1|X_2, X_3) + (w_2 - w_3)H(X_1, X_2) + w_3H(X_1, X_2, X_3) + (w_2 - w_3)H(X_1, X_2) + w_3H(X_1, X_2, X_3) + (w_2 - w_3)H(X_1, X_2|X_3) + w_3H(X_1, X_2, X_3) + (w_2 - w_3)H(X_1, X_2|X_3) + w_3H(X_1, X_2, X_3) + (w_2 - w_3)H(X_1, X_2|X_3) + \frac{1}{2}(w_1 - w_2 + w_3)H(X_1, X_3) + \frac{1}{2}(-w_1 + w_2 + w_3)H(X_1, X_2) + H(X_1, X_3)) = (w_1 - w_2)H(X_1|X_2, X_3) + (w_2 - w_3)H(X_1, X_2|X_3) + \frac{w_3H(X_1, X_2, X_3)}{(-w_1 + w_2 + w_3)H(X_3|X_1, X_2) + w_2H(X_1, X_2) + (w_1 - w_2)H(X_1, X_3) + \frac{w_3H(X_1, X_2) + w_3H(X_1, X_2) + w_3H(X_1, X_2) + (w_1 - w_2)H(X_1, X_3) + \frac{w_3H(X_1, X_2) + H(X_1, X_3)}{(-w_1 + w_2 + w_3)H(X_3|X_1, X_2) + w_3H(X_1, X_2) + (w_1 - w_2)H(X_1, X_2, X_3) + (w_2 - w_3)H(X_1, X_2) + (w_1 - w_2)H(X_1, X_2, X_3) + (w_2 - w_3)H(X_1, X_2) + (w_1 - w_2)H(X_1, X_2, X_3) +$$

Cases 2C and 5B:

$$\begin{split} & (w_1 - w_2) \, H \, (X_1 | X_{v_1}) + w_3 H \, (X_3 | X_{v_3}) + w_2 H \, (X_1, X_2) \\ & \geq (w_1 - w_2) \, H \, (X_1 | X_2, X_3) + (w_2 - w_3) \, H \, (X_1, X_2) \\ & + w_3 H \, (X_1, X_2, X_3) \\ & \geq (w_1 - w_2) \, H \, (X_1 | X_2, X_3) + (w_2 - w_3) \, H \, (X_1, X_2 | X_3) \\ & + w_3 H \, (X_1, X_2, X_3) . \end{split}$$

$$= (w_1 - w_2) H (X_1 | X_2, X_3) + (w_2 - w_3) (H (X_1 | X_3) + H (X_2 | X_3)) + w_3 H (X_1, X_2, X_3) \geq (w_1 - w_2) H (X_1 | X_2, X_3) + (w_2 - w_3) H (X_1, X_2 | X_3) + w_3 H (X_1, X_2, X_3). Cases 5A and 5C:$$

$$\begin{aligned} &(w_1 - w_2 - w_3) H (X_1 | X_{\nu_1}) + w_2 H (X_1, X_2) \\ &+ w_3 H (X_1, X_3) \\ &\geq (w_1 - w_2) H (X_1 | X_2, X_3) + (w_2 - w_3) H (X_1, X_2) \\ &+ w_3 (H (X_1, X_2) + H (X_1, X_3) - H (X_1)) \\ &\geq (w_1 - w_2) H (X_1 | X_2, X_3) + (w_2 - w_3) H (X_1, X_2) \\ &+ w_3 H (X_1, X_2, X_3) \\ &\geq (w_1 - w_2) H (X_1 | X_2, X_3) + (w_2 - w_3) H (X_1, X_2 | X_3) \\ &+ w_3 H (X_1, X_2, X_3). \end{aligned}$$

## APPENDIX C **PROOF OF LEMMA 9**

The following result is needed for the proof of Lemma 9. Lemma 15: Assume that  $H(X_V) = H(X_{V'})$  for all  $V, V' \subseteq [1:K]$  with |V| = |V'|. We have

$$\frac{H\left(X_{[1:i_1]}|X_{[i_1+1:j]}\right)}{i_1} \le \frac{H\left(X_{[1:i_2]}|X_{[i_2+1:j]}\right)}{i_2}$$

for any  $i_1, i_2, j \in [1 : K]$  such that  $i_1 \le i_2 \le j$ .

*Proof:* It suffices to consider the case  $i_1 < i_2$ . Note that

$$\begin{split} i_{2}H\left(X_{[1:i_{2}]}|X_{[i_{2}+1:j]}\right) \\ &= \sum_{k=1}^{i_{2}} H\left(X_{[1:i_{2}]}|X_{[i_{2}+1:j]}\right) \\ &= \sum_{k=1}^{i_{2}} H\left(X_{k}|X_{[i_{2}+1:j]}\right) \\ &+ \sum_{k=1}^{i_{2}} H\left(X_{[1:i_{2}]\setminus\{k\}}|X_{\{k\}\bigcup[i_{2}+1:j]}\right) \\ &\geq H\left(X_{[1:i_{2}]}|X_{[i_{2}+1:j]}\right) + i_{2}H\left(X_{[1:i_{2}-1]}|X_{[i_{2}:j]}\right). \end{split}$$

Therefore,

$$\frac{H\left(X_{[1:i_2-1]}|X_{[i_2:j]}\right)}{i_2-1} \le \frac{H\left(X_{[1:i_2]}|X_{[i_2+1:j]}\right)}{i_2}.$$

One can readily complete the proof via induction. Now we are ready to prove Lemma 9.

*Proof of Lemma 9:* Consider an arbitrary  $V \in \mathbb{V}_{K,\alpha}$ . Let  $V_1 \triangleq V \cap [1:l]$  and  $V_2 \triangleq V \setminus V_1$ . It suffices to show that

$$\sum_{k \in V_1} H\left(U_{k,\alpha} | U_{[k+1:\alpha],\alpha}\right) + |V_2| \frac{H\left(U_{[l+1:\alpha],\alpha}\right)}{\alpha - l}$$
  

$$\geq H\left(U_{[1:|V|],\alpha} | U_{[|V|+1:\alpha],\alpha}\right).$$
(52)

First consider the case  $V_i \neq \emptyset$ , i = 1, 2. Note that

$$\sum_{k \in V_{1}} H\left(U_{k,\alpha} | U_{[k+1:\alpha],\alpha}\right)$$

$$= \sum_{\tau=1}^{|V_{1}|} H\left(U_{\langle V_{1} \rangle_{\tau},\alpha} | U_{[\langle V_{1} \rangle_{\tau}+1:\alpha],\alpha}\right)$$

$$\geq \sum_{\tau=1}^{|V_{1}|} H\left(U_{\tau,\alpha} | U_{[\tau+1:\alpha],\alpha}\right)$$

$$= H\left(U_{[1:|V_{1}|],\alpha} | U_{[|V_{1}|+1:\alpha],\alpha}\right),$$
(53)

where (53) is due to the fact that  $\langle V_1 \rangle_{\tau} \ge \tau$  for  $\tau \in [1 : |V_1|]$ and that the source distribution is symmetrical entropy-wise. Moreover, we have

$$|V_{2}| \frac{H\left(U_{[l+1:\alpha]\alpha}\right)}{\alpha - l}$$

$$\geq |V_{2}| \frac{H\left(U_{[1:\alpha-l]\alpha}|U_{[\alpha-l+1:\alpha-|V_{1}|]\alpha}\right)}{\alpha - l}$$

$$\geq H\left(U_{[1:|V_{2}|]\alpha}|U_{[|V_{2}|+1:\alpha-|V_{1}|]\alpha}\right)$$

$$= H\left(U_{[1:|V_{2}|+1:|V_{1}|\alpha}|U_{[|V_{1}|+1:\alpha|\alpha}\right)$$
(55)
(56)

$$= H\left(U_{[|V_1|+1:|V|]a}|U_{[|V|+1:a]a}\right),\tag{56}$$

where (55) is due to Lemma 15 and the fact that  $\alpha - l \ge |V_2|$ . Combining (54) and (56) proves (52) for the case  $V_i \neq \emptyset$ , i = 1, 2.

Note that (52) degenerates to (54) when  $V_2 = \emptyset$  and degenerates to (56) when  $V_1 = \emptyset$ . This completes the proof of Lemma 9.

*Proof of (31):* Note that

$$\sum_{k=l_{\alpha}^{\mathbf{w}}+1}^{K} w_{k} = \sum_{k=l_{\alpha}^{\mathbf{w}}+1}^{K} \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}: k \in V} c_{V,\alpha}$$
$$= \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,\alpha} \sum_{k \in V \setminus [1:l_{\alpha}^{\mathbf{w}}]} 1$$
$$= (\alpha - l_{\alpha}^{\mathbf{w}}) \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,\alpha},$$

from which the desired result follows immediately. Proof of (32): Consider the following two cases. (*Case 1*)  $k \in [1:l_a^w]$ :

$$\sum_{V \in \mathbb{V}_{K,\alpha}: k \in V} c_{V,\alpha} = \sum_{i=k}^{l_{\alpha}^{W}} c_{[1:i],\alpha} + \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{W})}} c_{V,\alpha}$$
$$= w_{k} - \lambda_{\alpha}^{W} + \sum_{V \in \Omega_{K,\alpha}^{(W)}} c_{V,\alpha}$$
$$= w_{k}, \tag{57}$$

where (57) is due to (31).

(*Case 2*)  $k \in [l_{\alpha}^{\mathbf{w}} + 1 : K]$ :

$$\sum_{V \in \mathbb{V}_{K,\alpha}: k \in V} c_{V,\alpha} = \sum_{V \in \Omega_{K,\alpha}^{(\mathbb{I}^{W})}: k \in V} c_{V,\alpha} = w_{k}$$

Proof of (33): It suffices to verify that  $w_{l_{\alpha}^{w}} - \lambda_{\alpha}^{w} \ge 0$  when  $l_{\alpha}^{w} \ge 1$ . Indeed, this is a simple consequence of the fact that  $\mathbf{w} \in \mathbb{W}_{K,\alpha}^{(l_{\alpha}^{w})}$ . Proof of (34): Consider the following three cases. (Case 1)  $l_{\alpha-1}^{w} \le l_{\alpha}^{w} - 2$ : Note that

$$\sum_{k=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} (\alpha - 1 - k) c_{[1:k],\alpha} = (\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}) w_{l_{\alpha-1}^{\mathbf{w}}+1}$$
$$-\sum_{k=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} w_{k} - (\alpha - 1 - l_{\alpha}^{\mathbf{w}}) \lambda_{\alpha}^{\mathbf{w}}$$
(58)

and

$$(a - l_{a}^{\mathbf{w}}) \lambda_{a}^{\mathbf{w}} + \sum_{k=l_{a-1}^{\mathbf{w}}+1}^{l_{a}^{\mathbf{w}}} w_{k} = \sum_{k=l_{a}^{\mathbf{w}}+1}^{K} w_{k} + \sum_{k=l_{a-1}^{\mathbf{w}}+1}^{l_{a}^{\mathbf{w}}} w_{k}$$
$$= \sum_{k=l_{a-1}^{\mathbf{w}}+1}^{K} w_{k}$$
$$= (a - 1 - l_{a-1}^{\mathbf{w}}) \lambda_{a-1}^{\mathbf{w}}.$$
(59)

We have

$$\theta_{\alpha}^{\mathbf{w}} = \left(\lambda_{\alpha}^{\mathbf{w}} - \sum_{k=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} (\alpha - 1 - k) c_{[1:k],\alpha}\right) \frac{1}{\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}}$$
$$= \left(\lambda_{\alpha}^{\mathbf{w}} - (\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}) w_{l_{\alpha-1}^{\mathbf{w}}+1}\right)$$
$$+ \sum_{k=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} w_{k} + (\alpha - 1 - l_{\alpha}^{\mathbf{w}}) \lambda_{\alpha}^{\mathbf{w}}\right) \frac{1}{\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}}$$
(60)

$$= \left( \left( \alpha - l_{\alpha}^{\mathbf{w}} \right) \lambda_{\alpha}^{\mathbf{w}} + \sum_{k=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{*}} w_{k} - \left( \alpha - 1 - l_{\alpha-1}^{\mathbf{w}} \right) w_{l_{\alpha-1}^{\mathbf{w}}+1} \right) \frac{1}{\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}} = \left( \left( \alpha - 1 - l_{\alpha-1}^{\mathbf{w}} \right) \lambda_{\alpha-1}^{\mathbf{w}} - \left( \alpha - 1 - l_{\alpha-1}^{\mathbf{w}} \right) w_{l_{\alpha-1}^{\mathbf{w}}+1} \right) \\ \times \frac{1}{\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}} \tag{61} = \lambda_{\alpha-1}^{\mathbf{w}} - w_{l_{\alpha-1}^{\mathbf{w}}+1} \tag{62} = c_{\left[1:l_{\alpha-1}^{\mathbf{w}}\right], \alpha} - c_{\left[1:l_{\alpha-1}^{\mathbf{w}}\right], \alpha-1},$$

where (60) and (61) are due to (58) and (59), respectively. It can be verified that

$$(\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}) \lambda_{\alpha-1}^{\mathbf{w}} = \sum_{k=l_{\alpha-1}^{\mathbf{w}}+1}^{K} w_{k}$$

$$= \sum_{k=l_{\alpha-1}^{\mathbf{w}}+2}^{K} w_{k} + w_{l_{\alpha-1}^{\mathbf{w}}+1}$$

$$\ge (\alpha - 2 - l_{\alpha-1}^{\mathbf{w}}) w_{l_{\alpha-1}^{\mathbf{w}}+1} + w_{l_{\alpha-1}^{\mathbf{w}}+1}$$

$$= (\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}) w_{l_{\alpha-1}^{\mathbf{w}}+1}, \qquad (64)$$

where (63) follows from the fact that  $\mathbf{w} \in \mathbb{W}_{K,\alpha-1}^{(l_{\alpha-1}^{\mathbf{w}})}$ . Combining (62) and (64) proves  $\theta_{\alpha}^{\mathbf{w}} \ge 0$ . (*Case 2*)  $l_{\alpha-1}^{\mathbf{w}} = l_{\alpha}^{\mathbf{w}} - 1$ : Note that

$$(\alpha - l_{\alpha}^{\mathbf{w}}) \lambda_{\alpha}^{\mathbf{w}} = \sum_{k=l_{\alpha}^{\mathbf{w}}+1}^{K} w_{k}$$
$$= (\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}) \lambda_{\alpha-1}^{\mathbf{w}} - w_{l_{\alpha}^{\mathbf{w}}}$$
$$= (\alpha - l_{\alpha}^{\mathbf{w}}) \lambda_{\alpha-1}^{\mathbf{w}} - w_{l_{\alpha}^{\mathbf{w}}}.$$
(65)

We have

$$\begin{aligned}
\theta_{\alpha}^{\mathbf{w}} &= \left(\lambda_{\alpha}^{\mathbf{w}} - \left(\alpha - 1 - l_{\alpha}^{\mathbf{w}}\right)c_{\left[1:l_{\alpha}^{\mathbf{w}}\right],\alpha}\right)\frac{1}{\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}} \\
&= \left(\lambda_{\alpha}^{\mathbf{w}} - \left(\alpha - 1 - l_{\alpha}^{\mathbf{w}}\right)\left(w_{l_{\alpha}^{\mathbf{w}}} - \lambda_{\alpha}^{\mathbf{w}}\right)\right)\frac{1}{\alpha - l_{\alpha}^{\mathbf{w}}} \\
&= \lambda_{\alpha-1}^{\mathbf{w}} - w_{l_{\alpha}^{\mathbf{w}}} \\
&= c_{\left[1:l_{\alpha-1}^{\mathbf{w}}\right],\alpha} - c_{\left[1:l_{\alpha-1}^{\mathbf{w}}\right],\alpha-1},
\end{aligned}$$
(66)

where (66) is due to (65). The fact that  $\theta_{\alpha}^{\mathbf{w}} \geq 0$  follows by (64) and (66).

(*Case 3*)  $l_{\alpha-1}^{\mathbf{w}} = l_{\alpha}^{\mathbf{w}}$ : Note that

$$\theta_{\alpha}^{\mathbf{w}} = \frac{1}{\alpha - 1 - l_{\alpha - 1}^{\mathbf{w}}} \lambda_{\alpha}^{\mathbf{w}} \ge 0.$$

Moreover, we have

$$\frac{1}{\alpha - 1 - l_{\alpha - 1}^{\mathbf{w}}} \lambda_{\alpha}^{\mathbf{w}} = \frac{1}{\left(\alpha - 1 - l_{\alpha}^{\mathbf{w}}\right)\left(\alpha - l_{\alpha}^{\mathbf{w}}\right)} \sum_{k = l_{\alpha}^{\mathbf{w}} + 1}^{K} w_{k}$$
$$= \left(\frac{1}{\alpha - 1 - l_{\alpha}^{\mathbf{w}}} - \frac{1}{\alpha - l_{\alpha}^{\mathbf{w}}}\right) \sum_{k = l_{\alpha}^{\mathbf{w}} + 1}^{K} w_{k}$$
$$= \lambda_{\alpha - 1}^{\mathbf{w}} - \lambda_{\alpha}^{\mathbf{w}}$$
$$= c_{\left[1:l_{\alpha - 1}^{\mathbf{w}}\right], \alpha} - c_{\left[1:l_{\alpha - 1}^{\mathbf{w}}\right], \alpha - 1}.$$

Proof of (35): Consider the following two cases. (Case 1)  $l_{\alpha}^{\mathbf{w}} = 0$ :

$$\sum_{V \in \mathbb{V}_{K,\alpha}} c_{V,\alpha} = \sum_{V \in \Omega_{K,\alpha}^{(0)}} c_{V,\alpha}$$
$$= \frac{1}{\alpha} \sum_{k=1}^{K} w_k, \tag{67}$$

where (67) is due to (31). (*Case 2*)  $l_{\alpha}^{w} > 0$ :

$$\sum_{V \in \mathbb{V}_{K,a}} c_{V,a} = \sum_{k=1}^{I_a^w - 1} c_{[1:k]a} + c_{[1:I_a^w]a} + \sum_{V \in \Omega_{K,a}^{(l_a^w)}} c_{V,a}$$
$$= \sum_{k=1}^{I_a^w - 1} (w_k - w_{k+1}) + (w_{l_a^w} - \lambda_a^w) + \sum_{V \in \Omega_{K,a}^{(l_a^w)}} c_{V,a}$$
$$= \sum_{k=1}^{I_a^w - 1} (w_k - w_{k+1}) + (w_{l_a^w} - \lambda_a^w) + \lambda_a^w$$
(68)
$$= w_{1},$$

where (68) is due to (31).

# APPENDIX E Proof of Lemma 12

*Proof of Part (1) of Lemma 12:* Note that (26), (27), and (29) obviously hold. Moreover, (28) is implied by (34). Therefore, it suffices to verify (30).

Consider an arbitrary integer  $k \in [l_{\alpha-1}^{\mathbf{w}} + 1 : K]$ . We have

$$\sum_{\substack{V' \in \Omega_{K,\alpha-1}^{(l_{\alpha-1}^{\mathbf{w}})}: k \in V'}} \sum_{\substack{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}: V' \subseteq V}} \frac{c_{V,\alpha}}{\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}}$$

$$= \sum_{\substack{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}: k \in V}} \frac{\left| \left\{ V' \in \Omega_{K,\alpha-1}^{(l_{\alpha-1}^{\mathbf{w}})}: k \in V' \subseteq V \right\} \right|}{\alpha - 1 - l_{\alpha-1}^{\mathbf{w}}} c_{V,\alpha}$$

$$= \sum_{\substack{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}: k \in V}} c_{V,\alpha}.$$
(69)

Note that

$$\sum_{\substack{V' \in \Omega_{K,a-1}^{(l_{a-1}^{\mathbf{w}})} : k \in V'}} \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{V \in \Omega_{K,a}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,a} \sum_{i=l_{a-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} c_{[1:i],a}$$

$$\times \sum_{\tau=i+1}^{a} \mathcal{I} \left\{ V' = \langle V \rangle_{[1:a] \setminus \{\tau\}} \right\}$$

$$= \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{V \in \Omega_{K,a}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,a} \sum_{i=l_{a-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} c_{[1:i],a}$$

$$\times \sum_{\tau=i+1}^{a} \sum_{V' \in \Omega_{K,a-1}^{(l_{\alpha}^{\mathbf{w}})} : k \in V'} \mathcal{I} \left\{ V' = \langle V \rangle_{[1:a] \setminus \{\tau\}} \right\}.$$
(70)

Moreover,

$$\sum_{\tau=i+1}^{\alpha} \sum_{\substack{V' \in \Omega_{K,\alpha-1}^{\binom{l^{\mathbf{w}}}{k},\alpha-1}: k \in V'}} \mathcal{I}\left\{V' = \langle V \rangle_{[1:\alpha] \setminus \{\tau\}}\right\}$$
$$= \sum_{\tau=i+1}^{\alpha} \mathcal{I}\left\{k \in \langle V \rangle_{[1:\alpha] \setminus \{\tau\}}\right\}$$
$$= (\alpha - 1 - i) \mathcal{I}\left\{k \in V\right\} + \mathcal{I}\left\{k \in \langle V \rangle_{[1:i]}\right\},$$
$$V \in \Omega_{K,\alpha}^{\binom{l^{\mathbf{w}}}{k}}, \quad i \in [l^{\mathbf{w}}_{\alpha-1} + 1: l^{\mathbf{w}}_{\alpha}].$$
(71)

Therefore,

$$\sum_{\substack{V' \in \Omega_{K,a-1}^{(I_{a-1}^{\mathbf{w}})}: k \in V' \\ K, a-1}} \frac{1}{\lambda_{a}^{\mathbf{w}}} \sum_{V \in \Omega_{K,a}^{(I_{a}^{\mathbf{w}})}} c_{V,a} \sum_{i=l_{a-1}^{\mathbf{w}}+1}^{l_{a}^{\mathbf{w}}} c_{[1:i]a}$$

$$\times \sum_{\tau=i+1}^{a} \mathcal{I}\left\{V' = \langle V \rangle_{[1:a] \setminus \{\tau\}}\right\}$$

$$= \frac{1}{\lambda_{a}^{\mathbf{w}}} \sum_{V \in \Omega_{K,a}^{(I_{a}^{\mathbf{w}})}} c_{V,a} \sum_{i=l_{a-1}^{\mathbf{w}}+1}^{l_{a}^{\mathbf{w}}} c_{[1:i]a}$$

$$\times \left((a-1-i)\mathcal{I}\left\{k \in V\right\} + \mathcal{I}\left\{k \in \langle V \rangle_{[1:i]}\right\}\right)$$
(72)

$$= \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} (\alpha - 1 - i) c_{[1:i],\alpha} \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}:k \in V} c_{V,\alpha}$$
$$+ \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}:k \in V} c_{V,\alpha} \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} c_{[1:i],\alpha} \mathcal{I}\left\{k \in \langle V \rangle_{[1:i]}\right\},$$
(73)

where (72) is obtained by substituting (71) into (70). Combining (69) and (73) gives

$$\sum_{\substack{V'\in\Omega_{K,\alpha-1}^{(l_{\alpha-1}^{\mathbf{w}})}:k\in V'\\ +\frac{1}{\lambda_{\alpha}^{\mathbf{w}}}\sum_{V\in\Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}:k\in V}}c_{V,\alpha}\sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{\mathbf{w}}c_{[1:i],\alpha}\mathcal{I}\left\{k\in\langle V\rangle_{[1:i]}\right\}.$$
(74)

Now consider the following two cases. (*Case 1*)  $k \in [l_{\alpha-1}^{\mathbf{w}} + 1 : l_{\alpha}^{\mathbf{w}}]$ : We have

$$\sum_{\substack{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{W})}: k \in V \\ = \lambda_{\alpha}^{W}}} c_{V,\alpha} = \sum_{\substack{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{W})} \\ = \lambda_{\alpha}^{W}}} c_{V,\alpha}$$
(75)

and

$$\mathcal{I}\left\{k \in \langle V \rangle_{[1:i]}\right\} = \mathcal{I}\left\{k \in [1:i]\right\},\$$
$$V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}, \quad i \in \left[l_{\alpha-1}^{\mathbf{w}} + 1: l_{\alpha}^{\mathbf{w}}\right], \quad (76)$$

where (75) is due to (31). Continuing from (74),

$$\sum_{\substack{V' \in \Omega_{K,a-1}^{\binom{W}{a-1}}: k \in V'\\ = \sum_{\substack{V \in \Omega_{K,a}^{\binom{W}{a}}: k \in V\\ + \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{\substack{V \in \Omega_{K,a}^{\binom{W}{a}}: k \in V\\ V \in \Omega_{K,a}^{\binom{W}{a}: k \in V}} c_{V,\alpha} \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1} c_{[1:i],\alpha} \mathcal{I} \{k \in [1:i]\}}$$

$$(77)$$

$$= \sum_{\substack{V \in \Omega_{K,\alpha}^{(\mathbb{N})}: k \in V \\ u \in X_{\alpha}^{(\mathbb{N})}: k \in V}} c_{V,\alpha} + \frac{1}{\lambda_{\alpha}^{\mathbb{W}}} \sum_{i=k}^{a} c_{[1:i],\alpha} \sum_{\substack{V \in \Omega_{K,\alpha}^{(\mathbb{N})}: k \in V \\ v \in \Omega_{K,\alpha}^{(\mathbb{N})}: k \in V}} c_{V,\alpha}$$
$$= \lambda_{\alpha}^{\mathbb{W}} + \sum_{i=k}^{l_{\alpha}^{\mathbb{W}}} c_{[1:i],\alpha}$$
$$= w_{k},$$
(78)

where (77) and (78) are due to (76) and (75), respectively. (*Case 2*)  $k \in [l_{\alpha}^{\mathbf{w}} + 1 : K]$ : We have

$$\sum_{\substack{V'\in\Omega_{K,\alpha-1}^{(l_{\alpha-1}^{\mathbf{w}})}:k\in V'\\ = w_k,}} c_{V',\alpha-1} = \sum_{\substack{V\in\Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}:k\in V\\ = w_k,}} c_{V,\alpha}$$
(79)

where (79) follows by (74) and the fact that

$$\mathcal{I}\left\{k\in\langle V\rangle_{[1:i]}\right\}=0,\quad V\in\Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})},\quad i\in\left[l_{\alpha-1}^{\mathbf{w}}+1:l_{\alpha}^{\mathbf{w}}\right].$$

This completes the verification of (30).

Proof of Part (2) of Lemma 12: Note that

$$\sum_{\tau=i+1}^{|V|} H\left(X_{\langle V \rangle_{[1:|V|] \setminus \{\tau\}}}\right)$$

$$= \sum_{\tau=i+1}^{|V|} H\left(X_{\langle V \rangle_{[1:|V|] \setminus \{\tau\}}} |X_{\langle V \rangle_{[1:i]}}\right) + \sum_{\tau=i+1}^{|V|} H\left(X_{\langle V \rangle_{[1:i]}}\right)$$

$$= \sum_{\tau=i+1}^{|V|} H\left(X_{\langle V \rangle_{[1:|V|] \setminus \{\tau\}}} |X_{\langle V \rangle_{[1:i]}}\right) + (|V| - i) H\left(X_{\langle V \rangle_{[1:i]}}\right)$$

$$\geq (|V| - 1 - i) H\left(X_{V} |X_{\langle V \rangle_{[1:i]}}\right)$$

$$+ (|V| - i) H\left(X_{\langle V \rangle_{[1:i]}}\right)$$

$$= (|V| - 1 - i) H(X_{V}) + H\left(X_{\langle V \rangle_{[1:i]}}\right),$$

$$i \in [0: |V| - 1], \qquad (81)$$

where (80) is due to Han's inequality [16]. We have

$$\sum_{V' \in \Omega_{K,a-1}^{(\mathbf{v}_{a-1}^{\mathbf{w}})}} \frac{\frac{\theta_{a}^{\mathbf{w}}}{\lambda_{a}^{\mathbf{w}}}}{V \in \Omega_{K,a}^{(l_{a}^{\mathbf{w}})} : V' \subseteq V} C_{V,a} H(X_{V'})$$

$$= \frac{\theta_{a}^{\mathbf{w}}}{\lambda_{a}^{\mathbf{w}}} \sum_{V \in \Omega_{K,a}^{(l_{a}^{\mathbf{w}})}} C_{V,a} \sum_{V' \in \Omega_{K,a-1}^{(l_{a-1}^{\mathbf{w}})} : V' \subseteq V} H(X_{V'})$$

$$= \frac{\theta_{a}^{\mathbf{w}}}{\lambda_{a}^{\mathbf{w}}} \sum_{V \in \Omega_{K,a}^{(l_{a}^{\mathbf{w}})}} c_{V,a} \sum_{\tau = l_{a-1}^{\mathbf{w}} + 1} H\left(X_{\langle V \rangle_{[1:a] \setminus \{\tau\}}}\right)$$

$$\geq \frac{\theta_{a}^{\mathbf{w}}}{\lambda_{a}^{\mathbf{w}}} \sum_{V \in \Omega_{K,a}^{(l_{a}^{\mathbf{w}})}} c_{V,a}$$

$$\times \left( \left(a - 1 - l_{a-1}^{\mathbf{w}}\right) H(X_{V}) + H\left(X_{[1:l_{a-1}^{\mathbf{w}}]}\right) \right)$$
(82)

$$= \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{w})}} c_{V,\alpha} H(X_{V})$$

$$-\frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1} (\alpha - i - 1) c_{[1:i],\alpha} \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,\alpha} H(X_{V}) + \left( c_{[1:l_{\alpha-1}^{\mathbf{w}}],\alpha} - c_{[1:l_{\alpha-1}^{\mathbf{w}}],\alpha-1} \right) H\left( X_{[1:l_{\alpha-1}^{\mathbf{w}}]} \right),$$
(83)

where (82) follows by (81), and (83) is due to (31) and (34). Moreover,

$$\sum_{\substack{V' \in \Omega_{K,\alpha-1}^{\left(\frac{\mathbf{w}}{\alpha}\right)}} \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{V \in \Omega_{K,\alpha}^{\left(\frac{\mathbf{w}}{\alpha}\right)}} c_{V,\alpha}$$

$$\times \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} c_{[1:i],\alpha} \sum_{\tau=i+1}^{\alpha} \mathcal{I}\left\{V' = \langle V \rangle_{[1:\alpha] \setminus \{\tau\}}\right\} H\left(X_{V'}\right)$$

$$= \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{V \in \Omega_{K,\alpha}^{\left(\frac{\mathbf{w}}{\alpha}\right)}} c_{V,\alpha} \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} c_{[1:i],\alpha} \sum_{\tau=i+1}^{\alpha} H\left(X_{\langle V \rangle_{[1:\alpha] \setminus \{\tau\}}}\right)$$

$$\geq \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,\alpha} \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} c_{[1:i],\alpha} \times \left( (\alpha - 1 - i) H(X_{V}) + H(X_{[1:i]}) \right)$$
(84)  
$$= \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} (\alpha - 1 - i) c_{[1:i],\alpha} \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,\alpha} H(X_{V}) + \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} c_{[1:i],\alpha} H(X_{[1:i]}) \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,\alpha} + \frac{1}{\lambda_{\alpha}^{\mathbf{w}}} \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} (\alpha - 1 - i) c_{[1:i],\alpha} \sum_{V \in \Omega_{K,\alpha}^{(l_{\alpha}^{\mathbf{w}})}} c_{V,\alpha} H(X_{V}) + \sum_{i=l_{\alpha-1}^{\mathbf{w}}+1}^{l_{\alpha}^{\mathbf{w}}} c_{[1:i],\alpha} H(X_{[1:i]}),$$
(85)

where (84) and (85) are due to (81) and (31), respectively. Now one can readily complete the proof by combining (82) and (85) and invoking the fact that  $c_{[1:i],\alpha-1} = c_{[1:i],\alpha}$  when  $i \in [1:l_{\alpha-1}^{\mathbf{w}} - 1]$ .

#### REFERENCES

- D. Slepian and J. K. Wolf, "Noiseless coding of correlated information sources," *IEEE Trans. Inf. Theory*, vol. 19, no. 4, pp. 471–480, Jul. 1973.
- [2] T. M. Cover, "A proof of the data compression theorem of Slepian and Wolf for ergodic sources (Corresp.)," *IEEE Trans. Inf. Theory*, vol. 21, no. 2, pp. 226–228, Mar. 1975.
- [3] J. R. Roche, "Distributed information storage," Ph.D. dissertation, Dept. Statist., Stanford Univ., Stanford, CA, USA, 1992.
- [4] R. W. Yeung, "Multilevel diversity coding with distortion," *IEEE Trans. Inf. Theory*, vol. 41, no. 2, pp. 412–422, Mar. 1995.
- [5] R. C. Singleton, "Maximum distance q-nary codes," *IEEE Trans. Inf. Theory*, vol. 10, no. 2, pp. 116–118, Apr. 1964.
- [6] J. R. Roche, R. W. Yeung, and K. P. Hau, "Symmetrical multilevel diversity coding," *IEEE Trans. Inf. Theory*, vol. 43, no. 3, pp. 1059–1064, May 1997.
- [7] R. W. Yeung and Z. Zhang, "On symmetrical multilevel diversity coding," *IEEE Trans. Inf. Theory*, vol. 45, no. 2, pp. 609–621, Mar. 1999.
- [8] S. Mohajer, C. Tian, and S. N. Diggavi, "Asymmetric multilevel diversity coding and asymmetric Gaussian multiple descriptions," *IEEE Trans. Inf. Theory*, vol. 56, no. 9, pp. 4367–4387, Sep. 2010.
- [9] A. Balasubramanian, H. D. Ly, S. Li, T. Liu, and S. L. Miller, "Secure symmetrical multilevel diversity coding," *IEEE Trans. Inf. Theory*, vol. 59, no. 6, pp. 3572–3581, Jun. 2013.
- [10] J. Jiang, N. Marukala, and T. Liu, "Symmetrical multilevel diversity coding and subset entropy inequalities," *IEEE Trans. Inf. Theory*, vol. 60, no. 1, pp. 84–103, Jan. 2014.
- [11] C. Tian and T. Liu. (2015). "Multilevel diversity coding with regeneration." [Online]. Available: http://arxiv.org/abs/1503.00013
- [12] L. Song, J. Chen, and C. Tian, "Broadcasting correlated vector Gaussians," *IEEE Trans. Inf. Theory*, vol. 61, no. 5, pp. 2465–2477, May 2015.
- [13] I. Csiszar, "Linear codes for sources and source networks: Error exponents, universal coding," *IEEE Trans. Inf. Theory*, vol. 28, no. 4, pp. 585–592, Jul. 1982.
- [14] C. Tian, S. Mohajer, and S. N. Diggavi, "Approximating the Gaussian multiple description rate region under symmetric distortion constraints," *IEEE Trans. Inf. Theory*, vol. 55, no. 8, pp. 3869–3891, Aug. 2009.
- [15] J. Chen and T. Berger, "Robust distributed source coding," *IEEE Trans. Inf. Theory*, vol. 54, no. 8, pp. 3385–3398, Aug. 2008.
- [16] T. S. Han, "Nonnegative entropy measures of multivariate symmetric correlations," *Inf. Control*, vol. 36, no. 2, pp. 133–156, Feb. 1978.

**Zhiqing Xiao** received the B.S. degree from the Beijing University of Posts and Telecommunications, China, in 2011. He is currently a PhD candidate in the Department of Electronic Engineering, Tsinghua University. His research interest is network information theory.

**Jun Chen** (S'03–M'06) received the B.E. degree with honors in communication engineering from Shanghai Jiao Tong University, Shanghai, China, in 2001 and the M.S. and Ph.D. degrees in electrical and computer engineering from Cornell University, Ithaca, NY, in 2004 and 2006, respectively.

He was a Postdoctoral Research Associate in the Coordinated Science Laboratory at the University of Illinois at Urbana-Champaign, Urbana, IL, from September 2005 to July 2006, and a Postdoctoral Fellow at the IBM Thomas J. Watson Research Center, Yorktown Heights, NY, from July 2006 to August 2007. Since September 2007 he has been with the Department of Electrical and Computer Engineering at McMaster University, Hamilton, ON, Canada, where he is currently an Associate Professor. His research interests include information theory, wireless communications, and signal processing.

He received several awards for his research, including the Josef Raviv Memorial Postdoctoral Fellowship in 2006, the Early Researcher Award from the Province of Ontario in 2010, and the IBM Faculty Award in 2010. He is currently serving as an Associate Editor for Shannon Theory for the IEEE TRANSACTIONS ON INFORMATION THEORY. **Yunzhou Li** (M'06) received the Ph.D. degree from Tsinghua University in 2004. He is currently a professorship researcher at Tsinghua University. His research interests include wireless and mobile communications, such as WLAN and cellular systems, as well as coding theory.

Jing Wang (M'99) received the B.S. and M.S. degrees in electronic engineering from Tsinghua University, Beijing, China, in 1983 and 1986, respectively. He has been on the Faculty at Tsinghua University since 1986. He is currently a professor at the School of Information Science and Technology, Tsinghua University. He serves as the Vice Director of the Tsinghua National Lab for Information Science and Technology. His research interests are in the area of wireless communications, including transmission and networking technologies of 5G. He has published more than 150 conference and journal papers.